

### Trouds: Sourch Bata Sin

information provided may not be the most current.

Please download the latest datasheet of BNX005-01 from the official website of Murata Manufacturing

Note: If you have not downloaded this document from our official website, please note that the

http://www.murata.com/on.gh/products/productdatail?partno=PNY005.01

# BNX005-01










### **Applications**

| Unsuitable   | Please be sure to read and comply with     |  |
|--------------|--|--|
| Applications | these "Precautions for use."               |  |
|              | Consumer equipment, Medical                |  |
|              | equipment [GHTF A/B/C] except for          |  |
|              | implant & surgery & auto injector,         |  |
|              | Industrial equipment except for            |  |
|              | transportation & facility & energy         |  |
|              | equipment                                  |  |
| Specific     | Please refer to Our Website and            |  |
| Applications | specifications, etc. for information about |  |
|              | the performance, functions, quality,       |  |
|              | management, and safety required for        |  |
|              | the above applications, and use            |  |
|              | Products after confirming the              |  |
|              | performance and reliability of the actual  |  |
|              | Product.                                   |  |
| Recommended  | Canalimar aguinment                        |  |
| Applications | Consumer equipment                         |  |



### Appearance & Shape







### Packaging Information

| Packaging | Specifications | Standard<br>Packing<br>Quantity |
|-----------|----------------|---------------------------------|
| -         | Вох            | 100                             |



### **Features**

The block type "EMIFIL" BNX series incorporates through-type capacitor, monolithic chip capacitors and bead. The BNX is high performance for use in DC power circuits.

#### Features

- 1. The filter enables obtaining high insertion loss in wide frequency ranges from 1MHz to 1GHz.
- 2. Effective for impulse noise such as electrostatic discharge or spike noise.
- 3. There are no connection routes in the current circuits, thus ensuring highly reliable performance.

#### **Applications**

- 1. Displays (PDP/LCD-TV)
- 2. Digital AV equipment
- 3. Amusement equipment
- 4. PC peripheral equipment
- 5. Industry equipment

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

(in mm)

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BNX005-01

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BNX005-01 from the official website of Murata Manufacturing

http://www.murata.com/en-gb/products/productdetail?partno=BNX005-01



# **Specifications**

| Shape                          | Lead   |
|--------------------------------|--|
| Length                         | 12.0mm   |
| Length Tolerance               | ±0.5mm   |
| Width                          | 11.0mm   |
| Width Tolerance                | ±0.5mm   |
| Thickness                      | 13.5mm   |
| Thickness Tolerance            | max.   |
| Rated Current                  | 15A  |
| Operating Temperature<br>Range | -30°C to 85°C                                  |
| Mass(typ.)                     | 3.3g   |
| Rated Voltage                  | 50Vdc  |
| Withstanding Voltage           | 125Vdc   |
| Insulation Resistance(min.)    | 100ΜΩ  |
| Insertion Loss                 | 1MHz to 1GHz:40dB min.<br>(Line impedance=50Ω) |

2 of 3

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




# BNX005-01


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BNX005-01 from the official website of Murata Manufacturing

http://www.murata.com/en-gb/products/productdetail?partno=BNX005-01







**Insertion Loss Characteristics** 

**Equivalent Circuit** 

3 of 3

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

