

### Product Search Data Sheet

Note: This datasheet may be out of date.

Please download the latest datasheet of CSTCW33M3X51-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=CSTCW33M3X51-R0

# CSTCW33M3X51-R0










### **Applications**

| Unsuitable   | Please be sure to read and comply with     |
|--------------|--|
| Applications | these "Precautions for use."               |
|              | Consumer equipment                         |
|              | Please refer to Our Website and            |
|              | specifications, etc. for information about |
| Specific     | the performance, functions, quality,       |
| Specific     | management, and safety required for        |
| Applications | the above applications, and use            |
|              | Products after confirming the              |
|              | performance and reliability of the actual  |
|              | Product.                                   |



## Appearance & Shape







### Packaging Information

| Packaging | Specifications      | Standard<br>Packing<br>Quantity |
|-----------|---------------------|---------------------------------|
| R0        | 180mm Embossed Tape | 3000                            |



### **Features**

MURATA's package technology expertise has enabled the development of the Chip CERALOCK. High-density mounting can be realized because of the small package and the elimination of the need for an external load capacitor.

#### Features

- 1. Oscillation circuits do not require external load capacitors.
- 2. Available in a wide frequency range.
- 3. Extremely small and have a low profile.
- 4. No adjustment is necessary for oscillation circuits.

1 of 2

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





### Product Search Data Sheet

#### Note: This datasheet may be out of date. Please download the latest datasheet of CSTCW33M3X51-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=CSTCW33M3X51-R0

# CSTCW33M3X51-R0



# **Specifications**

| Product Type                | Ceramic Resonator |
|-----------------------------|-------------------|
| Troduct Type                | (CERALOCK)        |
| Series                      | CSTCW_X           |
| Frequency                   | 33.000MHz         |
| Frequency Tolerance         | +/-0.50% max.     |
| Operating Temperature Range | -20°C~80°C        |
| Frequency Shift by          |                   |
| Temperature                 | +/-0.20% max.     |
| remperature                 |                   |
| Frequency Aging             | +/-0.10% max.     |
| Resonant Impedance (R1)     | 50ohm max.        |
| Built-in Load Capacitance   | 6pF               |
| (CL1/CL2)                   | ОРГ               |
| Shape                       | SMD               |
| Wash                        | Not available     |
| L x W (size)                | 2.5x2.0mm         |
| Mass                        | 32mg              |

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

