

Product Search Data Sheet

PTGL07AR750M7B52A0

Discontinued RoHS

HS REACH


Applications

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
Specific Applications	Industrial Equipment
	Please refer to Our Website and
	specifications, etc. for information about
	the performance, functions, quality,
	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.



Appearance & Shape





Note: This datasheet may be out of date. Please download the latest datasheet of PTGL07AR750M7B52A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=PTGL07AR750M7B52A0

Packaging Information

Packaging	Specifications	Standard Packing Quantity
A0	Ammo Pack	1000



 Best suited to meet the requirements for power supplies and motor protection. Error-free operations are assured by rush current.
Circuit is protected until current is turned off.

3. Restores the original low resistance value automatically once the overload is removed.

4. Non-contact design leads to long life and no noise.

Durable and strong against mechanical vibration and shock because it is a solid element.

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





PTGL07AR750M7B52A0

Note: This datasheet may be out of date. Please download the latest datasheet of PTGL07AR750M7B52A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=PTGL07AR750M7B52A0

Specifications

Max. Voltage	125V
Hold Current(25°C)	82mA
Hold Current (2)	65mA
Measure Condition of Hold Current (2)	(at +60°C)
Trip Current(25°C)	142mA
Trip Current(2)	165mA
Measure Condition of Trip Current(2)	(at -10°C)
Max. Current	0.3A
Resistance (25°C)	75Ω
Resistance Value Tolerance (at 25°C)	±20%
Curie Point(typ.)	120°C
Power Consumption(typ)	1.3W
Operating Temperature Range	-10°C to 60°C
D- Outer Dimension	8mm
Thickness	6mm
F- Lead Space	5mm
d- Lead Diameter	0.6mm
Shape	Lead
Mass	0.81g
MSL	Ν

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Product Search Data Sheet


PTGL07AR750M7B52A0

Note: This datasheet may be out of date. Please download the latest datasheet of PTGL07AR750M7B52A0 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=PTGL07AR750M7B52A0







Resistance-Temperature Charac.



Operating Time (Typical Curve)

Protective Threshold Current Range

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



without advance notice. Please check with our sales representatives or product engineers before ordering.