

CSTNE12M2GH5L000R0


In Production Recommended RoHS REACH

### Applications

| Unsuitable   | Please be sure to read and comply with     |  |
|--------------|--|--|
| Applications | these "Precautions for use."               |  |
| Applications |  |  |
|              | Consumer equipment,Industrial              |  |
|              | equipment except for transportation &      |  |
|              | facility & energy equipment,Medical        |  |
|              | equipment [GHTF A/B],Mobile                |  |
|              | Electronics                                |  |
| Specific     | Please refer to Our Website and            |  |
| Applications | specifications, etc. for information about |  |
|              | the performance, functions, quality,       |  |
|              | management, and safety required for        |  |
|              | the above applications, and use            |  |
|              | Products after confirming the              |  |
|              | performance and reliability of the actual  |  |
|              | Product.                                   |  |

## Appearance & Shape






Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of CSTNE12M2GH5L000R0 from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=CSTNE12M2GH5L000R0

# Packaging Information

| Packaging | Specifications      | Standard<br>Packing<br>Quantity |
|-----------|---------------------|---------------------------------|
| R0        | 180mm Embossed Tape | 3000                            |



MURATA's frequency adjustment and packaging technology expertise has enabled the development of the chip CERALOCK.

#### Features

- 1. Oscillation circuits do not require external load capacitors.
- 2. Available for a wide frequency range.
- 3. Extremely small and have a low profile.
- 4. No adjustment is necessary for oscillation circuits.
- 5. Stable supply is ensured due to not using precious metal(Palladium).



#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

- without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of CSTNE12M2GH5L000R0 from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=CSTNE12M2GH5L000R0

# CSTNE12M2GH5L000R0

# Specifications

| Product Type                           | Ceramic Resonator<br>(CERALOCK) |
|--|---------------------------------|
| Series                                 | CSTNE_GH5L                      |
| Frequency                              | 12.288MHz                       |
| Frequency Tolerance                    | +/-0.07% max.                   |
| Operating Temperature<br>Range         | -40°C~85°C                      |
| Frequency Shift by<br>Temperature      | +/-0.11% max.                   |
| Frequency Aging                        | +/-0.07% max.                   |
| Resonant Impedance (R1)                | 30ohm max.                      |
| Built-in Load Capacitance<br>(CL1/CL2) | 33pF                            |
| Shape                                  | SMD                             |
| Wash                                   | Not available                   |
| L x W (size)                           | 3.2x1.3mm                       |
| Mass                                   | 11.73mg                         |

2 of 2

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

