

Note: This datasheet may be out of date. Please download the latest datasheet of CSTCR6M00G55B-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTCR6M00G55B-R0

CSTCR6M00G55B-R0














Applications

| Unsuitable | Please be sure to read and comply with | |
|--------------------------|--|--|
| Applications | these "Precautions for use." | |
| Specific Applications | Automotive powertrain/safety equipment | |
| | Please refer to Our Website and | |
| | specifications, etc. for information about | |
| | the performance, functions, quality, | |
| | management, and safety required for | |
| | the above applications, and use | |
| | Products after confirming the | |
| | performance and reliability of the actual | |
| | Product. | |



Appearance & Shape







Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|---------------------|---------------------------------|
| R0 | 180mm Embossed Tape | 3000 |



Features

MURATA's frequency adjustment and package technology expertise has enabled the development of the chip CERALOCK. This diverse series owes its development to MURATA's original mass production techniques and high reliability, and has achieved importance in the worldwide automotive market.

Features

- 1. The series has high reliability and is available for a wide temperature range.
- 2. Oscillation circuits do not require external load capacitors.
- 3. The series is available in a wide frequency range.
- 4. The resonators are extremely small and have a low profile.
- 5. No adjustment is necessary for oscillation circuits.

1 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: This datasheet may be out of date. $Please\ download\ the\ latest\ data sheet\ of\ CSTCR6M00G55B-R0\ from\ the\ official\ website\ of\ Murata$ Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTCR6M00G55B-R0

CSTCR6M00G55B-R0



Specifications

| Product Type | Ceramic Resonator | |
|-----------------------------|-------------------|--|
| Troduct Type | (CERALOCK) | |
| Series | CSTCR_G_B | |
| Frequency | 6.000MHz | |
| Frequency Tolerance | +/-0.50% max. | |
| Operating Temperature Range | -40°C~125°C | |
| Frequency Shift by | | |
| Temperature | +/-0.15% max. | |
| <u> </u> | | |
| Frequency Aging | +/-0.05% max. | |
| Resonant Impedance (R1) | 50ohm max. | |
| Built-in Load Capacitance | 39pF | |
| (CL1/CL2) | | |
| Shape | SMD | |
| Wash | available | |
| L x W (size) | 4.5x2.0mm | |
| Mass | 29mg | |

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

