

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW43SH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW43SH101XK2%23

"#"at the end indicates the package specification code.

For CAN









< List of part numbers with package codes >

DLW43SH101XK2B

DLW43SH101XK2K

DLW43SH101XK2L




#### **Applications**

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Automotive powertrain/safety equipment,	
	Automotive infotainment/comfort	
	equipment,Consumer equipment,	
	Medical equipment [GHTF A/B/C]	
	except for implant & surgery & auto	
	injector,Industrial Equipment	
Specific	Please refer to Our Website and	
Applications	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive powertrain/safety equipment,	
Applications	CAN [Controller Area Network],FlexRay	



### Appearance & Shape







### Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
К	330mm Embossed Tape	2500
L	180mm Embossed Tape	500

1 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Note: This datasheet may be out of date.

Please download the latest datasheet of DLW43SH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW43SH101XK2%23

"#"at the end indicates the package specification code.



1. Small size: L4.5xW3.2xT2.6mm (EIAcode: 1812)

Tolerance: 0.2mm

2. Common mode inductance items of 11,22,51,100microH, and they can be used for each applications.

**Applications** 

For Automotive.

Common mode noise suppression of automotive LAN for Flex Ray,  ${\sf CAN}.$ 

2 of 4

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW43SH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW43SH101XK2%23

"#"at the end indicates the package specification code.



### **Specifications**

Shape	SMD
Size Code (in mm)	4532
Size Code (in inch)	1812
Length	4.5mm
Length Tolerance	±0.2mm
Width	3.2mm
Width Tolerance	±0.2mm
Thickness	2.6mm
Thickness Tolerance	±0.2mm
Rated Current	200mA
Derating of Rated Current	No
Rated Voltage	50Vdc
Withstanding Voltage	125Vdc
DC Resistance(max.)	2Ω
DC Resistance	2.0Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 125°C
Mass(typ.)	0.17g
Number of Circuit	1
Common Mode Inductance	100µH-30%/+50% (at 1MHz)
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

3 of 4

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no space for \ detailed \ specifications.}$ 

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date.

Please download the latest datasheet of DLW43SH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW43SH101XK2%2

"#"at the end indicates the package specification code.

# Product Data



10000

10000

Common mode

1000

DLW43SH510XK2=DLW43SH101XK2

DLW43SH220XK2

DLW43SH110XK2

DLW43SH110XK2

DLW43SH220XK2

DLW43SH110XK2

DLW43SH110XK2

DLW43SH110XK2


DLW43SH110XK2

DLW43SH110XK2


Impedance-Frequency Characteristics

Impedance-Frequency Characteristics (Main Items)

#### ■ Equivalent Circuit (Note 1)



Note1: The Port/Pin No. of the Simulation Model provided by our company is as follows



Equivalent Circuit

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



4 of 4