

# BLM18BD121SN1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18BD121SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=BLM18BD121SN1%23

"#"at the end indicates the package specification code.







< List of part numbers with package codes > BLM18BD121SN1B

BLM18BD121SN1D

BLM18BD121SN1J




### **Applications**

Unsuitable	Please be sure to read and comply with		
Applications	these "Precautions for use."		
	Consumer equipment,Medical		
	equipment [GHTF A/B/C] except for		
	implant & surgery & auto injector,		
	Industrial equipment except for		
	transportation & facility & energy		
	equipment		
Specific	Please refer to Our Website and		
Applications	specifications, etc. for information about		
	the performance, functions, quality,		
	management, and safety required for		
	the above applications, and use		
	Products after confirming the		
	performance and reliability of the actual		
	Product.		
Recommended	Company of a surface of the surface		
Applications	Consumer equipment		



## Appearance & Shape











(in mm)



### **Packaging Information**

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000



#### **Features**

The chip ferrite beads BLM series is designed to work nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

BLM B series can minimize attenuation of the signal waveform due to its sharp impedance characteristics. Various impedances are available to match signal frequency.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance.

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BLM18BD121SN1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18BD121SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=BLM18BD121SN1%23

"#"at the end indicates the package specification code.



# **Specifications**

Shape	SMD
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.005g
Number of Circuit	1
Rated Current (at 125°C)	300mA
DC Resistance(max.)	0.4Ω
Impedance (at 100MHz)	120Ω
Impedance (at 100MHz) Tolerance	±25%
Size Code (in mm)	1608

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





# BLM18BD121SN1#


Note: This datasheet may be out of date.


Please download the latest datasheet of BLM18BD121SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=BLM18BD121SN1%23

"#"at the end indicates the package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

