

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18DN601SH1# from the official website of Murata Manufacturing Co., Ltd.

"#"at the end indicates the package specification code.

http://www.murata.com/en-sg/products/productdetail?partno=BLM18DN601SH1%23

BLM18DN601SH1#

In Production AEC-Q200 RoHS REACH

< List of part numbers with package codes > BLM18DN601SH1B BLM18DN601SH1D BL


BLM18DN601SH1J



Applications

Please be sure to read and comply with	
these "Precautions for use."	
Automotive powertrain/safety equipment,	
Automotive infotainment/comfort	
equipment,Consumer equipment,	
Medical equipment [GHTF A/B/C]	
except for implant & surgery & auto	
injector,Industrial Equipment	
Please refer to Our Website and	
specifications, etc. for information about	
the performance, functions, quality,	
management, and safety required for	
the above applications, and use	
Products after confirming the	
performance and reliability of the actual	
Product.	
Automotive powertrain/safety equipment	

Appearance & Shape



(in mm)



Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000



Features

Chip ferrite beads for high frequency noise suppression over a wide frequency range.

Features

- 1. High impedance characteristic in 1GHz or higher frequency
- 2. High impedance characteristic over a wide frequency band range of 100MHz to 6GHz
- 3. Low DC Resistance enables large Rated Current

Applications

1. Noise suppression for Automotive LED Lighting.

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





BLM18DN601SH1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18DN601SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=BLM18DN601SH1%23

"#"at the end indicates the package specification code.



Specifications

Shape	SMD
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.004g
Number of Circuit	1
Rated Current (at 85°C)	700mA
Rated Current (at 125°C)	450mA
DC Resistance(max.)	0.435Ω
Impedance (at 100MHz)	600Ω
Impedance (at 100MHz) Tolerance	±25%
Impedance (at 1GHz)	1500Ω
Impedance (at 1GHz) Tolerance	±30%
Size Code (in mm)	1608

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






BLM18DN601SH1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLM18DN601SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=BLM18DN601SH1%23


"#"at the end indicates the package specification code.





In operating temperature exceeding +85°C, derating of current is necessary for this series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics

Derating of Rated Current

(Resistance element becomes dominant at high frequencies.)

Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

