

Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BLM18AG221SN1# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=BLM18AG221SN1%23

#### "#"at the end indicates the package specification code.

In Production RoHS

HS REACH

BLM18AG221SN1#

< List of part numbers with package codes > BLM18AG221SN1B BLM18AG221SN1D BLM


BLM18AG221SN1J



### Applications

| Please be sure to read and comply with     |  |
|--|--|
| these "Precautions for use."               |  |
| Consumer equipment,Medical                 |  |
| equipment [GHTF A/B/C] except for          |  |
| implant & surgery & auto injector,         |  |
| Industrial equipment except for            |  |
| transportation & facility & energy         |  |
| equipment                                  |  |
| Please refer to Our Website and            |  |
| specifications, etc. for information about |  |
| the performance, functions, quality,       |  |
| management, and safety required for        |  |
| the above applications, and use            |  |
| Products after confirming the              |  |
| performance and reliability of the actual  |  |
| Product.                                   |  |
| Consumer equipment                         |  |
|  |  |

### Appearance & Shape



(in mm)



## **Packaging Information**

| Packaging | Specifications   | Standard<br>Packing<br>Quantity |
|-----------|------------------|---------------------------------|
| В         | Bulk(Bag)        | 1000                            |
| D         | 180mm Paper Tape | 4000                            |
| J         | 330mm Paper Tape | 10000                           |



#### Features

The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_Aseries generates an impedance from the relatively low frequencies. Therefore BLM\_Aseries is effective in noise suppression in a wide frequency range (30MHz to several hundred MHz).

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BLM18AG221SN1# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=BLM18AG221SN1%23

# BLM18AG221SN1#

"#"at the end indicates the package specification code.



## Specifications

| Shape                              | SMD            |
|------------------------------------|----------------|
| Size Code (in inch)                | 0603           |
| Length                             | 1.6mm          |
| Length Tolerance                   | ±0.15mm        |
| Width                              | 0.8mm          |
| Width Tolerance                    | ±0.15mm        |
| Thickness                          | 0.8mm          |
| Thickness Tolerance                | ±0.15mm        |
| Operating Temperature<br>Range     | -55°C to 125°C |
| Mass(typ.)                         | 0.005g         |
| Number of Circuit                  | 1              |
| Rated Current (at 125°C)           | 700mA          |
| DC Resistance(max.)                | 0.25Ω          |
| Impedance (at 100MHz)              | 220Ω           |
| Impedance (at 100MHz)<br>Tolerance | ±25%           |
| Size Code (in mm)                  | 1608           |

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Product Search Data Sheet




Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ \text{download} \ the \ latest \ \text{datasheet} \ of \ BLM18AG221SN1\# \ from \ the \ official \ website \ of \ Murata$ 


http://www.murata.com/en-us/products/productdetail?partno=BLM18AG221SN1%23


"#"at the end indicates the package specification code.



BLM18AG221SN1#







Impedance-Frequency Characteristics

Equivalent Circuit

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



3 of 3