

### Product Search Data Sheet

Note: This datasheet may be out of date.

Please download the latest datasheet of CDSCB10M7GF126-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=CDSCB10M7GF126-R0

# CDSCB10M7GF126-R0










## **Applications**

| Unsuitable               | Please be sure to read and comply with     |  |
|--------------------------|--|--|
| Applications             | these "Precautions for use."               |  |
| Specific<br>Applications | Consumer equipment                         |  |
|                          | Please refer to Our Website and            |  |
|                          | specifications, etc. for information about |  |
|                          | the performance, functions, quality,       |  |
|                          | management, and safety required for        |  |
|                          | the above applications, and use            |  |
|                          | Products after confirming the              |  |
|                          | performance and reliability of the actual  |  |
|                          | Product.                                   |  |



## Appearance & Shape







## Packaging Information

| Packaging | Specifications      | Standard<br>Packing<br>Quantity |
|-----------|---------------------|---------------------------------|
| R0        | 180mm Embossed Tape | 2000                            |



### **Features**

CDSCB10M7 series forms a resonator on a piezoelectric ceramic substrate. In combination with ICs, this type obtains stable demodulation characteristics in a wide bandwidth. They have 1.0mm max. thickness and small mounting area(4.5x2.0mm).

### Features

- 1. Compact and high reliability and recommended for automotive applications.
- 2. Can be combined with various ICs. The IC is determined by the last number in the part number.
- 3. Stable demodulation characteristics can be obtained without adjustment.
- 4. Stable temperature characteristics
- 5. Available lead (Pb) free solder reflow.

1 of 3

### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





### Product Search Data Sheet

Note: This datasheet may be out of date.  $Please\ download\ the\ latest\ data sheet\ of\ CDSCB10M7GF126-R0\ from\ the\ official\ website\ of\ Murata$ Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=CDSCB10M7GF126-R0

# CDSCB10M7GF126-R0



# **Specifications**

| Operating Temperature Range | -20°C to 80°C                     |
|-----------------------------|-----------------------------------|
| Shape                       | SMD                               |
| Elements                    | 1                                 |
| Center Frequency            | 10.700MHz                         |
| Nominal Center Value        | Yes                               |
| IC                          | NJM2295AV                         |
| IC Maker                    | JRC                               |
| S Curve(min.)               | 400mV mini.,[10.<br>700MHz±75kHz] |
| Detection Method            | quadrature type                   |
| Mass                        | 21.84mg                           |

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






### Note: This datasheet may be out of date. $Please\ download\ the\ latest\ data sheet\ of\ CDSCB10M7GF126-R0\ from\ the\ official\ website\ of\ Murata$ Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=CDSCB10M7GF126-R0

# CDSCB10M7GF126-R0



## **Product Data**



Measurement Circuit

3 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

