

Product Search Data Sheet

# SFZLA455KT2A-B0

REACH


Discontinued RoHS

### Applications

Unsuitable	Please be sure to read and comply with			
Applications	these "Precautions for use."			
	Consumer equipment			
	Please refer to Our Website and			
Onecifie	specifications, etc. for information about			
	the performance, functions, quality,			
Specific	management, and safety required for			
Applications	the above applications, and use			
	Products after confirming the			
	performance and reliability of the actual			
	Product.			



### Appearance & Shape



Note: This datasheet may be out of date. Please download the latest datasheet of SFZLA455KT2A-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=SFZLA455KT2A-B0

## Packaging Information

Packaging	Specifications	Standard Packing Quantity	
-B0	Bulk	200	



SFZLA series for AM use is one of the most recommendable intermediate filters, having such distinctive features as high selectivity, high stability, and adjustment-free operation. Additionally its easy matching with IC helps create an easy circuit design.

#### Features

1. Center frequency range between 450 to 470kHz are available standard tolerance of +/-2kHz.

2. For frequency synthesizers, center frequencies of 450, 459 and 468kHz are available standard tolerance of +/-1kHz.

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

(in mm)

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





## SFZLA455KT2A-B0

Note: This datasheet may be out of date. Please download the latest datasheet of SFZLA455KT2A-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=SFZLA455KT2A-B0



### Specifications

Operating Temperature Range	-20°C to 80°C			
Shape	Lead			
Elements	2			
Center Frequency	456.0kHz			
Center Frequency Tolerance	±2kHz			
Nominal Center Value	No			
3dB Bandwidth	7.0kHz±1.0kHz			
Selectivity(+)	16dB[fo+9kHz]			
Selectivity(-)	16dB[fo-9kHz]			
Spurious Attenuation	20dBmin.[within 0.1 to 3MHz]			
Insertion Loss	6.0dBmax.(at minimum loss point)			
Ripple	2.0dBmax.[within 3dBB.W.]			
GDT Deviation	20µsec.			
Input/Output Impedance	3000Ω			
Mass	726mg			

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Product Search Data Sheet





# SFZLA455KT2A-B0

Note: This datasheet may be out of date. Please download the latest datasheet of SFZLA455KT2A-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=SFZLA455KT2A-B0


Product Data





Frequency Characteristics (filter Only)





: 5.5.G. Output voitage

Measurement Circuit

Туре	SFULAB		SFZLA			
Item	7x7mm IFT					
Winding Specification	(1)-(2)	(2)—(3)	(4)—(6)	(1)-(2)	(2)—(3)	(4)—(6)
S(3) (2) (1) (6) (6) (6)	70T	115T	7T	68T	84T	14T
No load Qu	105			90		
Tuning Capacitance	180pF			180pF		

• Matching of CERAFIL® SFULA/SFZLA series with IFT is decided by the IFT secondary side impedance, [Z2]. The design target values of [Z2] are: For SFULA[]B :  $300\Omega$ For SF2LA[]A :  $1k\Omega$ 

### Recommended Ift

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

