

Note: This datasheet may be out of date. Please download the latest datasheet of CFWLA455KD1Y-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CFWLA455KD1Y-B0

CFWLA455KD1Y-B0










Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Consumer equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	



Appearance & Shape







Packaging Information

Packaging	Specifications	Standard Packing Quantity
-B0	Bulk	150



Features

CFWLA_Y series are high selectivity ceramic filters, which consist of 6 ceramic elements connected in a ladder form. They are most suitable for digital communications and mobile telephones because of their improved GDT characteristics.

Features

- 1. High selectivity
- 2. Avariety of bandwidths are available
- 3. Excellent GDT characteristics are available within pass
- 4. Easily mounted on a printed circuit board
- 5. Operating temperature range: -20 to +80 (degrees C), Storage temperature range: -40 to +85 (degrees C)

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





CFWLA455KD1Y-B0

Note: This datasheet may be out of date.

Please download the latest datasheet of CFWLA455KD1Y-B0 from the official website of Murata

Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=CFWLA455KD1Y-B0



Specifications

Operating Temperature Range	-20°C to 80°C	
Shape	Lead	
Elements	6	
Center Frequency	455.0kHz	
Center Frequency Tolerance	±1kHz	
Nominal Center Value	No	
6dB Bandwidth	fn±10.0kHzmin.	
Stop Bandwidth	25.0kHz	
Area of Stop Bandwidth	[within 50dB]	
Stop Band Attenuation	40dB[within fn±100kHz]	
Insertion Loss	8.0dB[at minimum loss point]	
Ripple	1.0dB[within fn±7kHz]	
GDT Deviation	30.0µs[within fn±7kHz]	
Input/Output Impedance	1500Ω	
Mass	690mg	

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date. Please download the latest datasheet of CFWLA455KD1Y-B0 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=CFWLA455KD1Y-B0

CFWLA455KD1Y-B0




Product Data





Frequency Characteristics

Spurious Response



Rg+R1=R2=Input/Output Impedance

Measurement Circuit

3 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

