

OBSOLETE PRODUCT
 Contact factory for replacement model



3 WATT UNREGULATED WIDE INPUT RANGE DC/DC CONVERTER

PWR72

FEATURES

- | Low Price
- | High Power Output: 3 Watts
- | Wide Input Voltage Range: 5VDC To 22VDC
- | Isolation Barrier 100% Tested Per UL544, VDE750, and CSA C22.2 Dielectric Withstand
- | Isolation Barrier Leakage Current 100% Tested At 240VAC: 3µA Max
- | Low Isolation Barrier Capacitance: 10pF
- | Single-Channel; Dual Output
- | Six-Sided Shielding

DESCRIPTION

The PWR72 is a 3W, single-channel, dual-output DC/DC converter designed for low cost spot power conversion and ground elimination applications.

It provides a plus and minus output voltage approximately equal to the input voltage magnitude. The PWR72 operates over a wide range of input voltages from 5VDC to 22VDC. Its unregulated outputs give the PWR72 high efficiency power conversion.

Surface-mounted devices and manufacturing processes are used in the PWR72 to give the user a device which is more environmentally rugged than most DC/DC converters. The use of surface-mounted technologies also gives the PWR72 superior isolation voltage. A third advantage of using surface-mounted technologies is low manufacturing cost.

MECHANICAL

Top View: 1.125" (28.28mm) width, 0.750" (19.05mm) height.

Side View: 0.561" (14.24mm) height, 0.270" (6.86mm) width, 0.170" (4.30mm) lead height.

Bottom View: Shows component layout on a grid.

NOTES: All dimensions are in inches (millimeters).
 GRID: 0.100 inches (2.54 millimeters)
 Marked with: specific model ordered, date code, job code.
 MATERIAL: Units are encapsulated in a low thermal resistance molding compound which has excellent chemical resistance, wide operating temperature range, and good electrical properties under high humidity environments. Lead material is brass with a solder plated surface to allow ease of solderability.

ELECTRICAL SPECIFICATIONS

At $T_A = +25^\circ\text{C}$, $+V_{IN} = 15\text{VDC}$, and $I_{OUT} = \pm 100\text{mA}$ unless otherwise noted.

PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
INPUT					
Rated Voltage			15		V _{DC}
Voltage Range		5		22	V _{DC}
Input Current	$I_{LOAD} = 0$		40		mA
	$I_{LOAD} = \text{Rated Load}$		280	330	mA
Ripple Current	$I_{LOAD} = 0$		15		mApk
	$I_{LOAD} = \text{Rated Load}$		150		mAp-p
ISOLATION					
Rated Voltage		1000			V _{DC}
Test Voltage	60s, 60Hz	3000			V _{pk}
Resistance			10		GW
Capacitance			10		pF
Leakage Current	$V_{ISO} = 240\text{VAC}, 60\text{Hz}$			3	μA
OUTPUT					
Rated Voltage			± 15		V _{DC}
Voltage Range	$I_{OUT} = \text{No Load}$	± 15		± 20	V _{DC}
	$I_{OUT} = \text{Rated Load}$	± 14.25		± 15.75	V _{DC}
Rated Power			3		W
Rated Current				100	mA
				200	mA
Current Range	Total of All Outputs			± 150	mA
	Each Output	0		300	mA
	Total of All Outputs	0			mA
Line Regulation	$10\text{V}_{DC} \leq V_{IN} \leq 18\text{V}_{DC}$		1.15		V/V
Load Regulation	$0\text{mA} \leq I_{LOAD} \leq 100\text{mA}$		15		mV/mA
Ripple Voltage	$I_{LOAD} = 0$		30		mVpk
	$I_{LOAD} = \text{Rated Load}$			150	mVpk
TEMPERATURE					
Specification		-25		+85	$^\circ\text{C}$
Operating		-40		+100	$^\circ\text{C}$

ABSOLUTE MAXIMUM RATINGS

Input Voltage.....	22V _{DC}
Output Short-Circuit Duration.....	Xs
Internal Power Dissipation.....	3W
Junction Temperature.....	+175 $^\circ\text{C}$
Package Thermal Resistance.....	13 $^\circ\text{C}/\text{W}$
Lead Temperature (Soldering, 10s).....	+300 $^\circ\text{C}$

ORDERING INFORMATION

Device Family _____	PWR 72 /H
PWR indicates DC/DC converter	
Model Number _____	
Reliability Screening _____	
No designator indicates standard manufacturing processing	



Murata Power Solutions, Inc.

11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A.

Tel: (508) 339-3000 (800) 233-2765 Fax: (508) 339-6356

www.murata-ps.com email: sales@murata-ps.com ISO 9001 & ISO 14001 REGISTERED

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.
© 2009 Murata Power Solutions, Inc.

USA: Mansfield (MA), Tel: (508) 339 3000, email: sales@murata-ps.com

Canada: Toronto, Tel: (866) 740 1232, email: toronto@murata-ps.com

UK: Milton Keynes, Tel: +44 (0)1908 615232, email: mk@murata-ps.com

France: Montigny Le Bretonneux, Tel: +33 (0)1 34 60 01 01, email: france@murata-ps.com

Germany: München, Tel: +49 (0)89-544334-0, email: ped.munich@murata-ps.com

Japan: Tokyo, Tel: 3-3779-1031, email: sales_tokyo@murata-ps.com

Osaka, Tel: 6-6354-2025, email: sales_osaka@murata-ps.com

China: Shanghai, Tel: +86 215 027 3678, email: shanghai@murata-ps.com

Guangzhou, Tel: +86 208 221 8066, email: guangzhou@murata-ps.com

Singapore: Parkway Centre, Tel: +65 6348 9096, email: singapore@murata-ps.com