Note: This datasheet may be out of date.

Please download the latest datasheet of PTGL10AR3R9M3B51A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=PTGL10AR3R9M3B51A0

### PTGL10AR3R9M3B51A0










### **Applications**


Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Industrial Equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	



### Appearance & Shape







(in mm)

# Packaging Information

Packaging	Specifications	Standard Packing Quantity
A0	Ammo Pack	1500



### **Features**

- 1. Best suited to meet the requirements for power supplies and motor protection. Error-free operations are assured by rush current.
- 2. Circuit is protected until current is turned off.
- 3. Restores the original low resistance value automatically once the overload is removed.
- 4. Non-contact design leads to long life and no noise.

  Durable and strong against mechanical vibration and shock because it is a solid element.

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$ 

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





#### Product Search Data Sheet

Note: This datasheet may be out of date.  $Please\ download\ the\ latest\ data sheet\ of\ PTGL10AR3R9M3B51A0\ from\ the\ official\ website\ of\ Muratangle and the statest and the stat$ Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=PTGL10AR3R9M3B51A0

## PTGL10AR3R9M3B51A0



### **Specifications**

Max. Voltage	56V
wax. voitage	300
Hold Current(25°C)	390mA
Hold Current (2)	300mA
Measure Condition of Hold Current (2)	(at +60°C)
Trip Current(25°C)	680mA
Trip Current(2)	800mA
Measure Condition of Trip Current(2)	(at -10°C)
Max. Current	2A
Resistance (25°C)	3.9Ω
Resistance Value Tolerance (at 25°C)	±20%
Curie Point(typ.)	120°C
Power Consumption(typ)	1.2W
Operating Temperature Range	-10°C to 60°C
D- Outer Dimension	10.5mm
Thickness	4mm
F- Lead Space	5mm
d- Lead Diameter	0.6mm
Shape	Lead
Mass	0.75g
MSL	N

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date. Please download the latest datasheet of PTGL10AR3R9M3B51A0 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en/products/productdetail?partno=PTGL10AR3R9M3B51A0

## PTGL10AR3R9M3B51A0




### **Product Data**





#### Resistance-Temperature Charac.



#### Operating Time (Typical Curve)

### Protective Threshold Current Range

3 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

