

Product Search Data Sheet

DLW43SH510XK2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW43SH510XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH510XK2%23

"#"at the end indicates the package specification code.


# In Production AEC-Q200 RoHS REACH


< List of part numbers with package codes > DLW43SH510XK2B DLW43SH510XK2K DLW43SH510XK2L



# Applications

| Unsuitable   | Please be sure to read and comply with     |  |
|--------------|--|--|
| Applications | these "Precautions for use."               |  |
|              | Automotive powertrain/safety equipment,    |  |
|              | Automotive infotainment/comfort            |  |
|              | equipment,Consumer equipment,              |  |
|              | Medical equipment [GHTF A/B/C]             |  |
|              | except for implant & surgery & auto        |  |
|              | injector,Industrial Equipment              |  |
| Specific     | Please refer to Our Website and            |  |
| Applications | specifications, etc. for information about |  |
|              | the performance, functions, quality,       |  |
|              | management, and safety required for        |  |
|              | the above applications, and use            |  |
|              | Products after confirming the              |  |
|              | performance and reliability of the actual  |  |
|              | Product.                                   |  |
| Recommended  | Automotive powertrain/safety equipment,    |  |
| Applications | CAN [Controller Area Network], FlexRay     |  |
|              |  |  |





| Packaging | Specifications      | Standard<br>Packing<br>Quantity |
|-----------|---------------------|---------------------------------|
| В         | Bulk(Bag)           | 100                             |
| К         | 330mm Embossed Tape | 2500                            |
| L         | 180mm Embossed Tape | 500                             |

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



(in mm)





Note: This datasheet may be out of date. Please download the latest datasheet of DLW43SH510XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH510XK2%23

"#"at the end indicates the package specification code.



1. Small size: L4.5xW3.2xT2.6mm (EIAcode: 1812) Tolerance: 0.2mm

DLW43SH510XK2#

2. Common mode inductance items of 11,22,51,100microH, and they can be used for each applications.

Applications For Automotive.

Common mode noise suppression of automotive LAN for Flex Ray, CAN.

2 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





DLW43SH510XK2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW43SH510XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH510XK2%23

"#"at the end indicates the package specification code.



# Specifications

| Shape  | SMD                     |
|--|-------------------------|
| Size Code (in mm)  | 4532                    |
| Size Code (in inch)  | 1812                    |
| Length   | 4.5mm                   |
| Length Tolerance   | ±0.2mm                  |
| Width  | 3.2mm                   |
| Width Tolerance  | ±0.2mm                  |
| Thickness  | 2.6mm                   |
| Thickness Tolerance  | ±0.2mm                  |
| Rated Current  | 230mA                   |
| Derating of Rated Current  | No                      |
| Rated Voltage  | 50Vdc                   |
| Withstanding Voltage   | 125Vdc                  |
| DC Resistance(max.)  | 1Ω                      |
| DC Resistance  | 1.0Ω max.               |
| Insulation Resistance(min.)  | 10ΜΩ                    |
| Operating Temperature<br>Range                                       | -40°C to 125°C          |
| Mass(typ.)   | 0.17g                   |
| Number of Circuit  | 1                       |
| Common Mode Inductance   | 51µH-30%/+50% (at 1MHz) |
| Operating Temperature<br>Range(Self-temperature rise<br>is included) | No                      |
| Brand  | Murata                  |

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.








Note: This datasheet may be out of date. Please download the latest datasheet of DLW43SH510XK2# from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en/products/productdetail?partno=DLW43SH510XK2%23

# "#"at the end indicates the package specification code.




DLW43SH510XK2#





Impedance-Frequency Characteristics

## Equivalent Circuit (Note 1)



**Equivalent Circuit** 

Impedance-Frequency Characteristics (Main Items)

4 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

