

NFL18ZT307H1A3#

Note: This datasheet may be out of date

Please download the latest datasheet of NFL18ZT307H1A3# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=NFL18ZT307H1A3%23

"#"at the end indicates the package specification code.









< List of part numbers with package codes > NFL18ZT307H1A3B NFL18ZT307H1A3D




Applications

Unsuitable	Places he cure to read and comply with	
	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Automotive infotainment/comfort	
	equipment,Consumer equipment,	
	Medical equipment [GHTF A/B/C]	
	except for implant & surgery & auto	
	injector,Industrial equipment except for	
	transportation & facility & energy	
	equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive infotainment/comfort	
Applications	equipment	



Appearance & Shape





Packaging Information

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000



Features

Features (NFL18ST_H/NFL18ZT series)

- 1. This product is compact size EMI suppression filter of 1.6x0.8x0.6mm. It has steep and deep insertion loss characteristics with T-type circuit.
- This product has large insertion loss in wide frequency range, results to good noise suppression effect.
- Sharp insertion loss curve enables both high noise suppression effect and low damage to signal waveform.
- 4. There are 6 line up of cutoff frequency between 50MHz to 500MHz.

1 of 3

Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





NFL18ZT307H1A3#

Note: This datasheet may be out of date.

Please download the latest datasheet of NFL18ZT307H1A3# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=NFL18ZT307H1A3%2

"#"at the end indicates the package specification code.



Specifications

Shape	SMD
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.1mm
Width	0.8mm
Width Tolerance	±0.1mm
Thickness	0.6mm
Thickness Tolerance	±0.1mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.004g
Number of Circuit	1
Rated Current	100mA
Rated Voltage	10Vdc
Withstanding Voltage	30Vdc
Insulation Resistance(min.)	1000ΜΩ
Insertion Loss	6dB max.(0 to 300MHz),30dB min.(1200 to 2000MHz)
Nominal Cut-off Frequency	300MHz
Capacitance	16pF
Inductance	74nH
Size Code (in mm)	1608

2 of 3

Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



^{1.} This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

^{2.} This datasheet has only typical specifications because there is no space for detailed specifications.



NFL18ZT307H1A3#


Note: This datasheet may be out of date


Please download the latest datasheet of NFL18ZT307H1A3# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=NFL18ZT307H1A3%2

"#"at the end indicates the package specification code.








Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



Equivalent Circuit

3 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

