

BLM31PG601SH1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM31PG601SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BLM31PG601SH1%23

"#"at the end indicates the package specification code.









< List of part numbers with package codes >

BLM31PG601SH1B

BLM31PG601SH1K

BLM31PG601SH1L




Applications

| Unsuitable | Please be sure to read and comply with | | |
|--------------|--------------------------------------------|--|--|
| Applications | these "Precautions for use." | | |
| | Automotive powertrain/safety equipment, | | |
| | Automotive infotainment/comfort | | |
| | equipment,Consumer equipment, | | |
| | Medical equipment [GHTF A/B/C] | | |
| | except for implant & surgery & auto | | |
| | injector,Industrial Equipment | | |
| Specific | Please refer to Our Website and | | |
| Applications | specifications, etc. for information about | | |
| | the performance, functions, quality, | | |
| | management, and safety required for | | |
| | the above applications, and use | | |
| | Products after confirming the | | |
| | performance and reliability of the actual | | |
| | Product. | | |
| Recommended | A. A | | |
| Applications | Automotive powertrain/safety equipment | | |



Appearance & Shape







Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|---------------------|---------------------------|
| В | Bulk(Bag) | 1000 |
| K | 330mm Embossed Tape | 10000 |
| L | 180mm Embossed Tape | 3000 |



Features

The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM_P series can be used in high current circuits due to its low DC resistance.

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





BLM31PG601SH1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM31PG601SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BLM31PG601SH1%23

"#"at the end indicates the package specification code.



Specifications

| Shape | SMD |
|---------------------------------|----------------|
| Size Code (in inch) | 1206 |
| Length | 3.2mm |
| Length Tolerance | ±0.2mm |
| Width | 1.6mm |
| Width Tolerance | ±0.2mm |
| Thickness | 1.1mm |
| Thickness Tolerance | ±0.2mm |
| Operating Temperature Range | -55°C to 125°C |
| Mass(typ.) | 0.025g |
| Number of Circuit | 1 |
| Rated Current (at 85°C) | 1.5A |
| Rated Current (at 125°C) | 1A |
| DC Resistance(max.) | 0.08Ω |
| Impedance (at 100MHz) | 600Ω |
| Impedance (at 100MHz) Tolerance | ±25% |
| Size Code (in mm) | 3216 |

2 of 3

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



BLM31PG601SH1#


Note: This datasheet may be out of date.

Please download the latest datasheet of BLM31PG601SH1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BLM31PG601SH1%23


"#"at the end indicates the package specification code.






In operating temperature exceeding +85°C, derating of current is necessary for BLM31PG series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics





Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

