Note: This datasheet may be out of date.

Please download the latest datasheet of PTGLCSAS1R2K3B51A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=PTGLCSAS1R2K3B51A0

## PTGLCSAS1R2K3B51A0










# **Applications**


Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
	Automotive powertrain/safety equipment
	Please refer to Our Website and
	specifications, etc. for information about
Specific	the performance, functions, quality,
Applications	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.



### Appearance & Shape







# 11

### Packaging Information

Packaging		Standard Packing Quantity
A0	Ammo Pack	1500



#### **Features**

- 1. Useful protective threshold current range with a wide temperature range.
- 2. Small fluctuation in the circuit due to resistance tolerance +/-10%
- 3. Quick operating time due to small size compared with conventional products.
- 4. Best suited to meet the requirements of power supply and motor protector. Error-free operation is assured by rush current.
- 5. Circuit is protected until current is turned off.
- 6. Restores the original low resistance value automatically once the overload is removed.
- 7. Non-contact design leads to long life and no noise.

  Durable and strong against mechanical vibration and shock because it is a solid element.
- 8. Lead (Pb) is not contained in the terminations.

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



Note: This datasheet may be out of date.

Please download the latest datasheet of PTGLCSAS1R2K3B51A0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=PTGLCSAS1R2K3B51A0

# PTGLCSAS1R2K3B51A0



# **Specifications**

Max. Voltage	51V
Hold Current(25°C)	749mA
Hold Current (2)	449mA
Measure Condition of Hold Current (2)	(at +85°C)
Hold Current (3)	315mA
Measure Condition of Hold Current (3)	(at +105°C)
Trip Current(25°C)	996mA
Trip Current(2)	1270mA
Measure Condition of Trip Current(2)	(at -40°C)
Max. Current	5A
Resistance (25°C)	1.2Ω
Resistance Value Tolerance (at 25°C)	±10%
Curie Point(typ.)	130℃
Power Consumption(typ)	2.4W
Operating Temperature Range	-40°C to 125°C
D- Outer Dimension	11.5mm
Thickness	3.5mm
H- Height	16.5mm
F- Lead Space	5mm
d- Lead Diameter	0.6mm
Shape	Lead
Mass	0.79g
MSL	N

2 of 3

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Data Chast

Note: This datasheet may be out of date.


Please download the latest datasheet of PTGLCSAS1R2K3B51A0 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-gb/products/productdetail?partno=PTGLCSAS1R2K3B51A0

# PTGLCSAS1R2K3B51A0




### **Product Data**





#### Resistance-Temperature Charac.



#### Protective Threshold Current Range

#### Operating Time (Typical Curve)

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

