

LQW15AN10NJ8Z#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW15AN10NJ8Z# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=LQW15AN10NJ8Z%23

"#"at the end indicates the package specification code.

0402(inch)/1005(mm) size, wound inductor.



















< List of part numbers with package codes > LQW15AN10NJ8ZB LQW15AN10NJ8ZD




Applications

	In the state of th	
Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Applications Specific Applications	Consumer equipment, Automotive infotainment/comfort equipment, Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector, Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive infotainment/comfort	
Applications	equipment	



Appearance & Shape







References

Packaging	Specifications	Standard Packing
В	Bulk(Bag)	Quantity 500
D	180mm Paper Tape	10000

Mass (typ.)	
1 piece	0.0009g

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LQW15AN10NJ8Z#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW15AN10NJ8Z# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=LQW15AN10NJ8Z%2

"#"at the end indicates the package specification code.



Specifications

L size	1.0±0.1mm
W size	0.6±0.1mm
T size	0.5±0.1mm
Size code inch (mm)	0402 (1005)
Inductance	10nH±5%
Inductance Test Frequency	100MHz
Rated current (Itemp) (Based on Temperature rise)	1400mA
Max. of DC resistance	0.081Ω
Operating Temperature Range(Self-temperature rise is not included)	-55°C to 125°C
Class of magnetic shield	Non-Shielded
Q(min.)	31
Q Test Frequency	250MHz
Self resonance frequency (min.)	6GHz
Brand	Murata
Series	LQW15AN_8Z

2 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LQW15AN10NJ8Z#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW15AN10NJ8Z# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=LQW15AN10NJ8Z%2

"#"at the end indicates the package specification code.




Notice For General

In operating temperatures exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in the chart according to the operating temperature.

Derating of Rated Current



3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



information provided may not be the most current.

Please download the latest datasheet of LQW15AN10NJ8Z# from the official website of Murata

Note: If you have not downloaded this document from our official website, please note that the

http://www.murata.com/en-gb/products/productdetail?partno=LQW15AN10NJ8Z%23


"#"at the end indicates the package specification code.


LQW15AN10NJ8Z#




Characteristic Data

The charts below may show another part number which shares its characteristics.







4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

