

Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of DLW21PH201XQ2# from the official website of Murata Manufacturing Co., Ltd.

"#"at the end indicates the package specification code.

http://www.murata.com/en-gb/products/productdetail?partno=DLW21PH201XQ2%23

DLW21PH201XQ2#

In Production AEC-Q200 RoHS REACH


< List of part numbers with package codes > DLW21PH201XQ2B DLW21PH201XQ2L

Applications

Unsuitable	Please be sure to read and comply with				
Applications	these "Precautions for use."				
	Automotive powertrain/safety equipment,				
	Automotive infotainment/comfort				
	equipment,Consumer equipment,				
	Medical equipment [GHTF A/B/C]				
	except for implant & surgery & auto				
	injector,Industrial Equipment				
Specific	Please refer to Our Website and				
Applications	specifications, etc. for information about				
	the performance, functions, quality,				
	management, and safety required for				
	the above applications, and use				
	Products after confirming the				
	performance and reliability of the actual				
	Product.				
Recommended	Automotive powertrain/safety equipment,				
Applications	PoC [Power over Coax],LVDS				

Appearance & Shape







Packaging Information

Γ			Standard
	Packaging	Specifications	Packing
			Quantity
	В	Bulk(Bag)	500
	L	180mm Embossed Tape	2000

Features

1. Small size: 2.0x1.2x1.2mm

2. High rated current available (500mA)

3. Available for high density mounting (Narrow pitch)

■Application

Measures against common mode noise in PoC circuit for high-speed

interfaces (SerDes) such as in-vehicle cameras.

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





DLW21PH201XQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW21PH201XQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=DLW21PH201XQ2%23

"#"at the end indicates the package specification code.



Specifications

Brand	Murata	

Shape	SMD		
Size Code (in mm)	2012		
Size Code (in inch)	0805		
Length	2.0mm		
Length Tolerance	±0.2mm		
Width	1.2mm		
Width Tolerance	±0.2mm		
Thickness	1.2mm		
Thickness Tolerance	±0.2mm		
Common Mode Impedance (at 100MHz)	200Ω		
Common Mode Impedance (at 100MHz) Tolerance	±25%		
Rated Current	500mA		
Derating of Rated Current	Yes (Over 105°C) *For details, please check the derating diagram.		
Rated Voltage	20Vdc		
Withstanding Voltage	50Vdc		
DC Resistance(max.)	0.168Ω		
DC Resistance	0.14Ω±20%		
Insulation Resistance(min.)	10ΜΩ		
Operating Temperature Range	-40°C to 125°C		
Mass(typ.)	0.011g		
Number of Circuit	1		
Operating Temperature Range(Self-temperature rise is included)	No		

2	of	3
---	----	---

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





DLW21PH201XQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW21PH201XQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=DLW21PH201XQ2%23


"#"at the end indicates the package specification code.






In operating temperature exceeding +105°C, derating of current is necessary for this series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics

Derating of Rated Current



Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

