

# NFE31PT470C1E9#

Note: This datasheet may be out of date

Please download the latest datasheet of NFE31PT470C1E9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=NFE31PT470C1E9%23

"#"at the end indicates the package specification code.







## < List of part numbers with package codes >

NFE31PT470C1E9B

NFE31PT470C1E9K

NFE31PT470C1E9L




### **Applications**

| Please be sure to read and comply with     |  |  |
|--|--|--|
| these "Precautions for use."               |  |  |
| Consumer equipment,Medical                 |  |  |
| equipment [GHTF A/B/C] except for          |  |  |
| implant & surgery & auto injector,         |  |  |
| Industrial equipment except for            |  |  |
| transportation & facility & energy         |  |  |
| equipment                                  |  |  |
| Please refer to Our Website and            |  |  |
| specifications, etc. for information about |  |  |
| the performance, functions, quality,       |  |  |
| management, and safety required for        |  |  |
| the above applications, and use            |  |  |
| Products after confirming the              |  |  |
| performance and reliability of the actual  |  |  |
| Product.                                   |  |  |
| Consumer equipment                         |  |  |
|  |  |  |



### Appearance & Shape







: Electrode



### Packaging Information

| Packaging | Specifications      | Standard Packing Quantity |
|-----------|---------------------|---------------------------|
| В         | Bulk(Bag)           | 500                       |
| K         | 330mm Embossed Tape | 8000                      |
| L         | 180mm Embossed Tape | 2000                      |



### **Features**

The chip "EMIFIL" NFE31PT is a small size T-type circuit EMI suppression filter.

#### Features

- 1. Its large rated current of 6A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4. 22 to 2,200pF lineups can be used in signal lines.

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





# NFE31PT470C1E9#

Note: This datasheet may be out of date.

Please download the latest datasheet of NFE31PT470C1E9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=NFE31PT470C1E9%23

"#"at the end indicates the package specification code.



### **Specifications**

| Shape                          | SMD           |
|--------------------------------|---------------|
| Size Code (in inch)            | 1206          |
| Length                         | 3.2mm         |
| Length Tolerance               | ±0.35mm       |
| Width                          | 1.6mm         |
| Width Tolerance                | ±0.15mm       |
| Thickness                      | 1.6mm         |
| Thickness Tolerance            | ±0.15mm       |
| Operating Temperature<br>Range | -40°C to 85°C |
| Mass(typ.)                     | 0.034g        |
| Number of Circuit              | 1             |
| Rated Current                  | 6A            |
| Rated Voltage                  | 25Vdc         |
| Withstanding Voltage           | 62.5Vdc       |
| Insulation Resistance(min.)    | 1000ΜΩ        |
| Capacitance                    | 47pF          |
| Capacitance Tolerance          | 50/-20%       |
| Size Code (in mm)              | 3216          |

2 of 3

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



# NFE31PT470C1E9#


Note: This datasheet may be out of date.


Please download the latest datasheet of NFE31PT470C1E9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=NEE31PT470C1E9%2

"#" at the end indicates the package specification code.








**Insertion Loss Characteristics** 

Insertion Loss Characteristics (Main Items)



**Equivalent Circuit** 

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

