

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of MYMGM1R816ELA5RN from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=MYMGM1R816ELA5RN

MYMGM1R816ELA5RN

7.5V to 15V input voltage, 16A, Buck Converter with PMBus and 125degC Tj



Applications

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
	Consumer equipment,Industrial
	Equipment
	Please refer to Our Website and
	specifications, etc. for information about
Specific	the performance, functions, quality,
Applications	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.
	Processor [ASIC / FPGA / xPU],Optical
Recommended	Backbone network,Optical Module,
Applications	Server,Storage,Switch,Base Station,
	Industrial Equipment




Features

Input voltage ranges from 7.5 to 15V Settable output voltage from 0.7 to 1.8V Up to 16Aof output current Quick response to load change Size 10.5 x 9.0 x 5.0mm High efficiency of 94.0% (max.) Over Current (OC) /Voltage (OV), Under Voltage (UV) protection and Over Temperature protection (OT). ON/OFF control (Positive logic) Power Good (PGOOD) signal PMBus interface available



Appearance & Shape





1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





MYMGM1R816ELA5RN

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of MYMGM1R816ELA5RN from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=MYMGM1R816ELA5RN



Specifications

lout(A)Max	16A
Vin(V)	7.5V to 15V
Vin(V)typ	12V
Vout(V)	0.7V to 1.8V
Vout(V)typ	1V
LineRegulation (%)	-0.5% to 0.5%
LoadRegulation (%)	-0.5% to 0.5%
Outputs (#)	1
Efficiency (%)	87%
Switching frequency (kHz)	400kHz
Size(mm)W	9.0mm
Size(mm)L	10.5mm
Size(mm)T	5.0mm
Operatingtemperature(degC)	-40°C to 105°C
Circuit topology	Buck(Step-down)
Package	SMD
Туре	Modules (integrated components)
Productseries	MYMGM
Product Series Features	MYMGM series which is POL (Point of Load) is single output MonoBK with PMBus
Brand	Murata

2 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

