



Note: This datasheet may be out of date.

Please download the latest datasheet of CSTCR6M00G15C99-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=CSTCR6M00G15C99-R0

CSTCR6M00G15C99-R0










Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Automotive powertrain/safety equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual	
	Product.	



Appearance & Shape







Packaging Information

Packaging	Specifications	Standard Packing Quantity
R0	180mm Embossed Tape	3000



Features

MURATA's frequency adjustment and packaging technology expertise has enabled the development of the chip CERALOCK. This diverse series owes its development to MURATA's original mass production techniques and high reliability, and has achieved importance in the worldwide automotive market.

Features

- 1. High accuracy resonators whose total tolerance is available for less than +-3,000ppm.
- 2. High reliability and available for a wide temperature range.
- 3. Oscillation circuits do not require external load capacitors.
- 4. Available for a wide frequency range.
- 5. Extremely small and have a low profile.
- 6. No adjustment is necessary for oscillation circuits.

1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Product Search Data Sheet

Note: This datasheet may be out of date. $Please\ download\ the\ latest\ data sheet\ of\ CSTCR6M00G15C99-R0\ from\ the\ official\ website\ of\ Murata$ Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=CSTCR6M00G15C99-R0

CSTCR6M00G15C99-R0



Specifications

Draduot Type	Ceramic Resonator	
Product Type	(CERALOCK)	
Series	CSTCR_G_C	
Frequency	6.000MHz	
Frequency Tolerance	+/-0.10% max.	
Operating Temperature	-40°C~125°C	
Range		
Frequency Shift by	1,10,400/	
Temperature	+/-0.13% max.	
Frequency Aging	+/-0.07% max.	
Resonant Impedance (R1)	50ohm max.	
Built-in Load Capacitance	39pF	
(CL1/CL2)	1 90pi	
Shape	SMD	
Wash	available	
L x W (size)	4.5x2.0mm	
Mass	32mg	

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

