

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15AG601SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BLM15AG601SN1%23

# BLM15AG601SN1#

"#"at the end indicates the package specification code.

In Production RoHS

HS REACH

< List of part numbers with package codes > BLM15AG601SN1B BLM15AG601SN1D BLM


BLM15AG601SN1J



## Applications

d and comply with	Unsuitable	
use."	Applications	
,Medical		
B/C] except for		
uto injector,		
except for		
y & energy		
ebsite and	Specific	
information about	Applications	
tions, quality,		
ety required for		
s, and use		
ing the		
bility of the actual		
	Recommended	
Consumer equipment		
information about tions, quality, fety required for s, and use hing the ibility of the actual	Applications	

Appearance & Shape



(in mm)



# Packaging Information

Packaging	Specifications	Standard Packing
В	Bulk(Bag)	Quantity 1000
D	180mm Paper Tape	10000
J	330mm Paper Tape	50000



### Features

The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_Aseries generates an impedance from the relatively low frequencies. Therefore BLM\_Aseries is effective in noise suppression in a wide frequency range (30MHz to several hundred MHz).

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





BLM15AG601SN1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15AG601SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BLM15AG601SN1%23

"#"at the end indicates the package specification code.



# Specifications

Shape	SMD
Size Code (in inch)	0402
Length	1.0mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.5mm
Thickness Tolerance	±0.05mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.001g
Number of Circuit	1
Rated Current (at 125°C)	300mA
DC Resistance(max.)	0.52Ω
Impedance (at 100MHz)	600Ω
Impedance (at 100MHz) Tolerance	±25%
Size Code (in mm)	1005

2 of 3

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Product Search Data Sheet




BLM15AG601SN1#


**Product Data** 

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15AG601SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=BLM15AG601SN1%23

"#"at the end indicates the package specification code.





Impedance-Frequency Characteristics

**Equivalent Circuit** 

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



3 of 3