

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN85NJ0Z# from the official website of Murata

"#"at the end indicates the package specification code.

For Power Choke















< List of part numbers with package codes >

LQW18CN85NJ0ZB

LQW18CN85NJ0ZD

LQW18CN85NJ0ZJ




Applications

11	DI	
Unsuitable	Please be sure to read and comply with	
Applications	plications these "Precautions for use."	
Specific Applications	Consumer equipment, Automotive	
	infotainment/comfort equipment,Medical	
	equipment [GHTF A/B/C] except for	
	implant & surgery & auto injector,	
	Industrial equipment except for	
	transportation & facility & energy	
	equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive infotainment/comfort	
Applications	equipment	



Appearance & Shape





1 of 5

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN85NJ0Z# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18CN85NJ0Z%23

"#"at the end indicates the package specification code.



References

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

Mass (typ.)		
1 piece	0.004g	

2 of 5

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN85NJ0Z# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18CN85NJ0Z%23

"#"at the end indicates the package specification code.



Specifications

	10:045
L size	1.6±0.15mm
W size	0.8±0.15mm
T size	0.8±0.15mm
Size code inch (mm)	0603 (1608)
Inductance	85nH±5%
Inductance Test Frequency	10MHz
Rated current (Itemp) (Based on Temperature rise)	1400mA
Max. of DC resistance	0.06Ω
Operating Temperature Range(Self-temperature rise is not included)	-40°C to 125°C
Class of magnetic shield	Non-Shielded
Self resonance frequency (min.)	1380MHz
Brand	Murata
Series	LQW18CN_0Z

3 of 5

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN85NJ0Z# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18CN85NJ0Z%2

"#"at the end indicates the package specification code.




Notice For General

In operating temperatures exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in the chart according to the operating temperature.

Derating of Rated Current



4 of 5

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of LQW18CN85NJ0Z# from the official website of Murata


"#"at the end indicates the package specification code.





Characteristic Data

LQW18CN85NJ0Z#

The charts below may show another part number which shares its characteristics.







5 of 5

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

