

# DLW21PH201XQ2#

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW21PH201XQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW21PH201XQ2%23

"#"at the end indicates the package specification code.









< List of part numbers with package codes > DLW21PH201XQ2B DLW21PH201XQ2L



### **Applications**

Please be sure to read and comply with
these "Precautions for use."
Automotive powertrain/safety equipment,
Automotive infotainment/comfort
equipment,Consumer equipment,
Medical equipment [GHTF A/B/C]
except for implant & surgery & auto
injector,Industrial Equipment
Please refer to Our Website and
specifications, etc. for information about
the performance, functions, quality,
management, and safety required for
the above applications, and use
Products after confirming the
performance and reliability of the actual
Product.
Automotive powertrain/safety equipment,
PoC [Power over Coax],LVDS



## **Packaging Information**

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	500
L	180mm Embossed Tape	2000



### **Features**

- 1. Small size: 2.0x1.2x1.2mm
- 2. High rated current available (500mA)
- 3. Available for high density mounting (Narrow pitch)
- ■Application


Measures against common mode noise in PoC circuit for high-speed

interfaces (SerDes) such as in-vehicle cameras.



## Appearance & Shape





1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





# DLW21PH201XQ2#

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW21PH201XQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW21PH201XQ2%2

"#"at the end indicates the package specification code.



## Specifications

Shape	SMD
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.2mm
Width Tolerance	±0.2mm
Thickness	1.2mm
Thickness Tolerance	±0.2mm
Common Mode Impedance (at 100MHz)	200Ω
Common Mode Impedance (at 100MHz) Tolerance	±25%
Rated Current	500mA
Derating of Rated Current	Yes (Over 105°C) *For details, please check the derating diagram.
Rated Voltage	20Vdc
Withstanding Voltage	50Vdc
DC Resistance(max.)	0.168Ω
DC Resistance	0.14Ω±20%
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 125°C
Mass(typ.)	0.011g
Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No

ı		
	Brand	Murata
	2.4	11101101101

2 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



# DLW21PH201XQ2#

Note: This datasheet may be out of date.


Please download the latest datasheet of DLW21PH201XQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW21PH201XQ2%23

"#"at the end indicates the package specification code.




### **Product Data**




In operating temperature exceeding +105°C, derating of current is necessary for this series.

Please apply the derating curve shown in chart according to the operating temperature.

#### Derating of Rated Current



### Impedance-Frequency Characteristics



### **Derating of Rated Current**

#### **Equivalent Circuit**

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

