

## DSS1NB32A101Q55#

Note: This datasheet may be out of date

Please download the latest datasheet of DSS1NB32A101Q55# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DSS1NB32A101Q55%2

"#"at the end indicates the package specification code.







# < List of part numbers with package codes > DSS1NB32A101Q55B



### **Applications**

| Unsuitable   | Please be sure to read and comply with     |
|--------------|--|
| Applications | these "Precautions for use."               |
|              | Consumer equipment,Medical                 |
|              | equipment [GHTF A/B/C] except for          |
|              | implant & surgery & auto injector,         |
|              | Industrial equipment except for            |
|              | transportation & facility & energy         |
|              | equipment                                  |
| Specific     | Please refer to Our Website and            |
| Applications | specifications, etc. for information about |
|              | the performance, functions, quality,       |
|              | management, and safety required for        |
|              | the above applications, and use            |
|              | Products after confirming the              |
|              | performance and reliability of the actual  |
|              | Product.                                   |
| Recommended  | Canadiana                                  |
| Applications | Consumer equipment                         |
|              |  |



## **Packaging Information**

|   | Packaging | Specifications | Standard<br>Packing |
|---|-----------|----------------|---------------------|
| ı |           |                | Quantity            |
|   | В         | Bulk(Bag)      | 250                 |



### **Features**

DSS1 series is a compact, high performance lead type 3 terminal capacitor which can be mounted in 2.54mm pitch.


Its three terminal structure enables nice high frequency performance.

Wide capacitance variation enables flexible selection for various noise frequencies. High speed mounting is available with automatic insertion machine.



## Appearance & Shape





1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





## DSS1NB32A101Q55#

Note: This datasheet may be out of date.

Please download the latest datasheet of DSS1NB32A101Q55# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DSS1NB32A101Q55%2

"#"at the end indicates the package specification code.



## **Specifications**

| Shape                          | Lead                               |
|--------------------------------|------------------------------------|
| Length                         | 8.5mm                              |
| Length Tolerance               | max.                               |
| Width                          | 3.5mm                              |
| Width Tolerance                | max.                               |
| Thickness                      | 7.5mm                              |
| Thickness Tolerance            | max.                               |
| Rated Current                  | 6A                                 |
| Operating Temperature<br>Range | -40°C to 85°C                      |
| Mass(typ.)                     | 0.45g                              |
| Number of Circuit              | 1                                  |
| Insulation Resistance(min.)    | 1000ΜΩ                             |
| Rated Voltage                  | 100Vdc                             |
| Withstanding Voltage           | 250Vdc                             |
| Capacitance                    | 100pF                              |
| Capacitance Tolerance          | ±10%                               |
| Structure/Shape                | Small type beads inside (straight) |

2 of 3

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



## DSS1NB32A101Q55#


Note: This datasheet may be out of date.


Please download the latest datasheet of DSS1NB32A101Q55# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DSS1NB32A101Q55%2

"#"at the end indicates the package specification code.








**Insertion Loss Characteristics** 

Insertion Loss Characteristics (Main Items)



**Equivalent Circuit** 

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

