

NDL0505SC

In Production

Recommended

RoHS


Applications

Unsuitable Applications	Please be sure to read and comply with these "Precautions for use."
Specific Applications	Consumer equipment, Industrial Equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.

Features

5V 400mA, Isolated 2W Single Output 1kVDC, DC-DC Converter
4.5-9V Input

Appearance & Shape



Attention

- 1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2.This datasheet has only typical specifications because there is no space for detailed specifications.
Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

NDL0505SC



Specifications

Output power (W)Max	2W
Vin(V)	4.5V to 9V
Vin(V)typ	5V
Vout(V)	5V
Vout(V)typ	5V
LineRegulation (%)	-0.2% to 0.2%
LoadRegulation (%)	0.5%
Isolation Voltage (V)	1000V
Efficiency (%)	66%
Size(mm)W	21.8mm
Size(mm)L	9.2mm
Size(mm)T	11.1mm
Operatingtemperature(degC)	-40°C to 85°C
Outputs (#)	1
Iout(A)Max	0.4A
Package	SIP
Productseries	NDL
Product Series Features	Isolated 2W Wide Input Single Output DC-DC Converters
Regulation	Regulated
Brand	Murata Power Solutions

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.