

Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of CSTNE14M0V53C000R0 from the official website of Murata

w.murata.com/en/products/productdetail?partno=CSTNE14M0V53C000R0


CSTNE14M0V53C000R0



Applications

Unsuitable	Please be sure to read and comply with these "Precautions for use."	
Applications		
	Automotive powertrain/safety equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
Chapifia	the performance, functions, quality,	
Specific Applications	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	

Appearance & Shape



3.0 max.	01010
0.50 (ref.)	0.50 (ref.)
(3) (2) (1) 0.4±0.1 0.4±0.1 0.4±0.1 ++ + +	(1): Input (2): GND (3): Output
+++++++++++++++++++++++++++++++++++++++	(i) Supplier (ii): Supplier (iii): Frequency Marking * : EIAJ Monthly Code
0.4±0.1 1.2±0.1 1.2±0.1	L (in mm)

Packaging Information

Packag	ling	Specifications	Standard Packing Quantity
R0		180mm Embossed Tape	3000



MURATA's package technology expertise has enabled the development of the Chip CERALOCK.

This diverse series owes its development to MURATA's original mass production techniques and high reliability, and has achieved importance in the worldwide automotive market.

Features

- 1. High reliability and available for a wide temperature range.
- 2. Oscillation circuits do not require external load capacitors.
- 3. Available for a wide frequency range.
- 4. Extremely small and have a low profile.
- 5. No adjustment is necessary for oscillation circuits.
- 6. Stable supply is ensured due to not using precious metal(Palladium).

1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





CSTNE14M0V53C000R0

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of CSTNE14M0V53C000R0 from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=CSTNE14M0V53C000R0

Specifications

Product Type	Ceramic Resonator (CERALOCK)
Series	CSTNE_V_C
Frequency	14.000MHz
Frequency Tolerance	+/-0.50% max.
Operating Temperature Range	-40°C~125°C
Frequency Shift by Temperature	+/-0.15% max.
Frequency Aging	+/-0.10% max.
Resonant Impedance (R1)	40ohm max.
Built-in Load Capacitance (CL1/CL2)	15pF
Shape	SMD
Wash	available
L x W (size)	3.2x1.3mm
Mass	16.972mg

2 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

