

DLW5ATN501TQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5ATN501TQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW5ATN501TQ2%23

"#"at the end indicates the package specification code.

In Production RoHS REACH

< List of part numbers with package codes > DLW5ATN501TQ2B DLW5ATN501TQ2K I

DLW5ATN501TQ2L



### Applications


Please be sure to read and comply with	
these "Precautions for use."	
Consumer equipment,Medical	
equipment [GHTF A/B/C] except for	
implant & surgery & auto injector,	
Industrial equipment except for	
transportation & facility & energy	
equipment	
Please refer to Our Website and	
specifications, etc. for information about	
the performance, functions, quality,	
management, and safety required for	
the above applications, and use	
Products after confirming the	
performance and reliability of the actual	
Product.	
Consumer equipment	



## Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
К	330mm Embossed Tape	2500
L	180mm Embossed Tape	700

# Appearance & Shape



1 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Product Search Data Sheet

# DLW5ATN501TQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5ATN501TQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW5ATN501TQ2%23

"#"at the end indicates the package specification code.



Low profile (h=2.35mm) chip common mode choke coil. Suitable for noise suppression at DC power lines.

Features

- 1. Low profile (h=2.35mm)
- 2. Small size (5.0x3.6mm)
- 3. Large Current Available (2A to 5A)
- 4. Operating Temperature Range: -40°C to +105°C

Applications

- Noise suppression for power line
- 1. Power line equipment -DC-DC converters -Battery chargers
- 2. Portable equipment
- -PDAs (Personal Digital Assistants) -Note PCs
- -Printers

2 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: This datasheet may be out of date. Please download the latest datasheet of DLW5ATN501TQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW5ATN501TQ2%23

# DLW5ATN501TQ2#

### "#"at the end indicates the package specification code.



### Specifications

Shape	SMD
Size Code (in mm)	5036
Size Code (in inch)	2014
Length	5.0mm
Length Tolerance	±0.3mm
Width	3.6mm
Width Tolerance	±0.3mm
Thickness	2.2mm
Thickness Tolerance	±0.15mm
Common Mode Impedance (at 100MHz)	500Ω
Common Mode Impedance (at 100MHz) Tolerance	(Тур.)
Common Mode Impedance (at 10MHz)	55Ω
Common Mode Impedance (at 10MHz) Tolerance	±25%
Rated Current	2A
Derating of Rated Current	Yes (Over 85℃) *For details, please check the derating diagram.
Rated Voltage	100Vdc
Withstanding Voltage	250Vdc
DC Resistance(max.)	0.056Ω
DC Resistance	0.056Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 105℃
Mass(typ.)	0.14g

Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.








DLW5ATN501TQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5ATN501TQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW5ATN501TQ2%23

"#"at the end indicates the package specification code.

# Product Data



DLW5ATN231TQ2

DLW5ATN501 DLW5ATN401TO2

10000


1000

Common mode

Impedance-Frequency Characteristics


In operating temperature exceeding +85°C, derating of current is necessary for DLW5AT series (105 degree C available type). Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



### Derating of Rated Current

Impedance-Frequency Characteristics (Main Items)



### **Equivalent Circuit**

4 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

