

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN55NJ0Z# from the official website of Murata

http://www.murata.com/en-sg/products/productdetail?partno=LQW18CN55NJ0Z%2

"#"at the end indicates the package specification code.

#### For Power Choke















### < List of part numbers with package codes >

LQW18CN55NJ0ZB

LQW18CN55NJ0ZD

LQW18CN55NJ0ZJ




### **Applications**

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Consumer equipment, Automotive infotainment/comfort equipment, Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector, Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product	
Recommended	Automotive infotainment/comfort	
Applications	equipment	
	l ' '	



### Appearance & Shape





1 of 5

#### Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN55NJ0Z# from the official website of Murata

http://www.murata.com/en-sq/products/productdetail?partno=LQW18CN55NJ0Z%2

"#"at the end indicates the package specification code.



### References

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

Mass (typ.)	
1 piece	0.004g

2 of 5

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN55NJ0Z# from the official website of Murata

http://www.murata.com/en-sg/products/productdetail?partno=LQW18CN55NJ0Z%2

"#"at the end indicates the package specification code.



# **Specifications**

L size	1.6±0.15mm
W size	0.8±0.15mm
T size	0.8±0.15mm
Size code inch (mm)	0603 (1608)
Inductance	55nH±5%
Inductance Test Frequency	10MHz
Rated current (Itemp) (Based on Temperature rise)	1500mA
Max. of DC resistance	0.045Ω
Operating Temperature Range(Self-temperature rise is not included)	-40°C to 125°C
Class of magnetic shield	Non-Shielded
Self resonance frequency (min.)	1600MHz
Brand	Murata
Series	LQW18CN_0Z

3 of 5

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18CN55NJ0Z# from the official website of Murata

http://www.murata.com/en-sg/products/productdetail?partno=LQW18CN55NJ0Z%2

"#"at the end indicates the package specification code.




### Notice For General

In operating temperatures exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in the chart according to the operating temperature.

#### Derating of Rated Current



4 of 5

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of LQW18CN55NJ0Z# from the official website of Murata


"#"at the end indicates the package specification code.


## LQW18CN55NJ0Z#




### Characteristic Data

The charts below may show another part number which shares its characteristics.







5 of 5

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

