

Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of MGN1D050603MC from the official website of Murata

MGN1D050603MC



Recommended

New





Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Industrial	
	Equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
Specific	the performance, functions, quality,	
Applications	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Gate driver power supply	
Applications	Gate driver power suppry	



Features

6V/-3V,111mA/111mA, Isolated 1W Dual Output 3kVAC, DC-DC Converter, 4.5-5.5V Input.



Appearance & Shape



1 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of MGN1D050603MC from the official website of Murata

http://www.murata.com/en-sg/products/productdetail?partno=MGN1D050603M

MGN1D050603MC



Specifications

Output power (W)Max	1W
Isolation Voltage (V)	3000Vac
Continuous Barrier Withstand Voltage(V)	1100V
Isolation capacitance(pF)	2.5pF
Vin(V)	4.5V to 5.5V
Vin(V)typ	5V
Vout(V)typ	6V
LineRegulation (%)	-0.2% to 0.2%
LoadRegulation (%)	1%
Efficiency (%)	62%
Size(mm)W	12.0mm
Size(mm)L	16.0mm
Size(mm)T	4.25mm
Operatingtemperature(degC)	-40°C to 105°C
Outputs (#)	2
lout(A)Max	0.111A
Package	SMD
Productseries	MGN1

Product Series Features	The MGN1 series of DC-DC converters is ideal for powering 'high side' and 'low side' gate drive circuits for GaN in bridge circuits. A choice of output voltages allows optimum drive levels for best system efficiency. The MGN1 series is characterised for high isolation requirements commonly seen in bridge circuits used in motor drives and inverters, while the MGN1 industrial grade temperature rating and construction gives long service life and reliability.
Safety Approval	UL62368-1
Vout2 (V)	-3V
LineRegulation2 (%)	-3.5% to 3.5%
LoadRegulation2 (%)	10%
lout2(A)Max	0.111A
Brand	Murata Power Solutions

2 of 2

Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

