

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of LFB18868MBG9E212 from the official website of Murata

# LFB18868MBG9E212












### **Applications**

Unsuitable	Please be sure to read and comply with		
Applications	these "Precautions for use."		
	Consumer equipment,Industrial		
	Equipment,Medical equipment [GHTF		
	A/B],Mobile Electronics		
	Please refer to Our Website and		
Cifi-	specifications, etc. for information about		
Specific	the performance, functions, quality,		
Applications	management, and safety required for		
	the above applications, and use		
	Products after confirming the		
	performance and reliability of the actual		
	Product.		
Recommended	Consumer equipment,Industrial		
	Equipment,Medical equipment [GHTF		
Applications	A/B],Mobile Electronics		



## Appearance & Shape





### Packaging Information

Packaging	Specifications	Standard Packing Quantity
-	180mm Paper Tape	4000



### **Features**

Ultra-small, low-profiled, lightweight chip filters based on ceramic multilayer technology.

Extremely ultra-small band-pass filters.

- 1. Ultra-small, low-profiled, lightweight band-pass filters.
- 2. Absolutely no adjustment required.
- 3. Reflow solderable.
- 4. Available in tape and reel packagings for automatic mounting.

1 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





### Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LFB18868MBG9E212 from the official website of Murata

# LFB18868MBG9E212



# **Specifications**

Applications	SUB1G(TI CC1310)
Nominal Center Frequency (fo)	869.50MHz
Bandwidth(BW)	fo±6.50MHz
Insertion Loss in BW I)	1.9dB max. (at 25°C)
Insertion Loss in BW II)	2.1dB max. (-40 ~ +85°C)
Attenuation(Absolute Value)	20.0dB min. at 1726.00 to
1)	1856.00MHz
Attenuation(Absolute Value)	40.0dB min. at 2589.00 to
II)	2784.00MHz
Attenuation(Absolute Value)	33.0dB min. at 3452.00 to
III)	3712.00MHz
Unbalance Impedance (Nom.)	50Ω
Power Capacity	500mW
Operating Temperature	-40°C to 85°C
Range	-40 C to 65 C
L x W (size)	1.60x0.80mm
Thickness(max.)	0.65mm

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

