

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata

"#"at the end indicates the package specification code.

http://www.murata.com/en-sg/products/productdetail?partno=NFE31PT101C1E9%23

NFE31PT101C1E9#

In Production RoHS REACH

< List of part numbers with package codes > NFE31PT101C1E9B NFE31PT101C1E9K


NFE31PT101C1E9L



Applications

Please be sure to read and comply with	
these "Precautions for use."	
Consumer equipment,Medical	
equipment [GHTF A/B/C] except for	
implant & surgery & auto injector,	
Industrial equipment except for	
transportation & facility & energy	
equipment	
Please refer to Our Website and	
specifications, etc. for information about	
the performance, functions, quality,	
management, and safety required for	
the above applications, and use	
Products after confirming the	
performance and reliability of the actual	
Product.	
O	
Consumer equipment	

Appearance & Shape



Electrode (in mm)



Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
К	330mm Embossed Tape	8000
L	180mm Embossed Tape	2000



Features

The chip "EMIFIL" NFE31PT is a small size T-type circuit EMI suppression filter.

Features

- 1. Its large rated current of 6A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4. 22 to 2,200pF lineups can be used in signal lines.

1	of	3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





NFE31PT101C1E9#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata

http://www.murata.com/en-sg/products/productdetail?partno=NFE31PT101C1E9%23

"#"at the end indicates the package specification code.



Specifications

Shape	SMD
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.35mm
Width	1.6mm
Width Tolerance	±0.15mm
Thickness	1.6mm
Thickness Tolerance	±0.15mm
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.034g
Number of Circuit	1
Rated Current	6A
Rated Voltage	25Vdc
Withstanding Voltage	62.5Vdc
Insulation Resistance(min.)	1000ΜΩ
Capacitance	100pF
Capacitance Tolerance	80/-20%
Size Code (in mm)	3216

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

Product Search Data Sheet



Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of NFE31PT101C1E9# from the official website of Murata


http://www.murata.com/en-sg/products/productdetail?partno=NFE31PT101C1E9%23


"#"at the end indicates the package specification code.



Product Data


NFE31PT101C1E9#





Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

