

NNOVATOR IN ELECTRONICS

Note: This datasheet may be out of date.

Please download the latest datasheet of IRA-S410ST01 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=IRA-S410ST01





IRA-S410ST01







Applications

| Unsuitable | Please be sure to read and comply with | |
|--------------------------|--|--|
| Applications | these "Precautions for use." | |
| Specific Applications | Consumer equipment | |
| | Please refer to Our Website and | |
| | specifications, etc. for information about | |
| | the performance, functions, quality, | |
| | management, and safety required for | |
| | the above applications, and use | |
| | Products after confirming the | |
| | performance and reliability of the actual | |
| | Product. | |
| Recommended | Intrusion detection,Security Equipment, | |
| Applications | Light | |



Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|----------------|---------------------------------|
| - | Вох | 100 |




Features

Excellent Sensitivity & S/N ratio (Signal/Noise) Excellent Quality



Appearance & Shape





1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





IRA-S410ST01

Note: This datasheet may be out of date.

Please download the latest datasheet of IRA-S410ST01 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=IRA-S410ST01



Specifications

| Shape | Lead |
|--------------------------------|-----------------------------|
| Dimensions | TO-5(φ9.2x4.7mm) |
| Output Type | Analog |
| Electrode | (2.3(gap0.3)x1.0mm)x2 |
| Responsivity(typ.) | 7.0mV |
| Supply Voltage Range | 2V to 15V |
| Field of View | theta1=38deg.,theta2=45deg. |
| Operating Temperature Range | -40°C to 70°C |
| Storage Temperature Range | -40°C to 85°C |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Product Search Data Sheet


Note: This datasheet may be out of date. Please download the latest datasheet of IRA-S410ST01 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=IRA-S410ST01


IRA-S410ST01







Pyroelectric Elements(Electrode Dimension)



Optical Filter characteristics

Test system of Responsivity

3 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

