

Note: This datasheet may be out of date. Please download the latest datasheet of TZR1Z040A001R00 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=TZR1Z040A001R00

TZR1Z040A001R00










Appearance & Shape







Features

- 1. Ultra-small and thin with external dimensions of
- 1.5(W)x1.7(L)x0.85(H)mm

(80% less in volume than the current product).

2. Unique construction with no plastic material provides superior soldering heat

resistance to maintain excellent characteristic performance after reflow Idering.

3. Suitable for high frequency circuit due to high self-resonant

(6.2GHz of TZR1Z010 at 1.0pF setting).



Packaging Information

Packaging	Specifications	Standard Packing Quantity
R00	180mm Embossed Tape	3000

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date. Please download the latest datasheet of TZR1Z040A001R00 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=TZR1Z040A001R00

TZR1Z040A001R00



Specifications

Shape	SMD	
Operating Temperature	-25°C to 85°C	
Range	-25 C to 65 C	
Thickness	0.85mm	
Thickness Tolerance	±0.05	
Rated Voltage	25Vdc	
Cmin.(max.)	1.5pF	
Cmax.	4pF	
Cmax. Tolerance	+100/-0%	
Adjustment Direction	Тор	
тс	NP0±500ppm/°C	
Q	300min. at 1MHz, Cmax.	
Withstanding Voltage	55Vdc	
Insulation Resistance(min.)	10000ΜΩ	
Torque	0.1 to 1.0mNm	
Mass	0.009g	

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



TZR1Z040A001R00

Note: This datasheet may be out of date.

head size as the driver below.


Screwdriver for Manual Adjustment Murata Part No.: KMDR160


Please download the latest datasheet of TZR1Z040A001R00 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=TZR1Z040A001R00



Product Data






Please use the following recommended screwdriver. You can order this driver with part number below. Though you can also adjust the capacitance value by


commercial products, please use one which has the same

Constructions





Recommended Screwdriver



Frequency Characteristics

Temp. Coeff. Characteristics

3 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

