

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ \text{download} \ the \ latest \ data sheet \ of \ LQM18NNR56K00\# \ from \ the \ of ficial \ website \ of \ Murata$

http://www.murata.com/en-us/products/productdetail?partno=LQM18NNR56K00%23

"#"at the end indicates the package specification code.

Size Code 1608 (0603) in mm (in inch)


LQM18NNR56K00#





< List of part numbers with package codes > LQM18NNR56K00B LQM18NNR56K00D LQM18NNR56K00J

Applications

	A		
Unsuitable	Please be sure to read and comply with		
Applications	these "Precautions for use."		
	Consumer equipment,Medical		
	equipment [GHTF A/B/C] except for		
	implant & surgery & auto injector,		
	Industrial equipment except for		
	transportation & facility & energy		
	equipment		
Specific	Please refer to Our Website and		
Applications	specifications, etc. for information about		
	the performance, functions, quality,		
	management, and safety required for		
	the above applications, and use		
	Products after confirming the		
	performance and reliability of the actual		
	Product.		
Recommended	Consumer equipment		
Applications	Consumer equipment		









Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



1 of 4



Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQM18NNR56K00# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=LQM18NNR56K00%23

LQM18NNR56K00#

"#"at the end indicates the package specification code.



References

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

Mass (typ.)	
1 piece	0.005g

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

2 of 4



LQM18NNR56K00#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ download \ the \ latest \ data sheet \ of \ LQM18NNR56K00\# \ from \ the \ of \ ficial \ website \ of \ Murata$

http://www.murata.com/en-us/products/productdetail?partno=LQM18NNR56K00%23

"#"at the end indicates the package specification code.



Specifications

L size	1.6±0.15mm
W size	0.8±0.15mm
T size	0.8±0.15mm
Size code inch (mm)	0603 (1608)
Inductance	560nH±10%
Inductance Test Frequency	25MHz
Rated current (Isat) (Based on Inductance change)	35mA
Rated current (Itemp) (Based on Temperature rise)	35mA
Max. of DC resistance	1.55Ω
Operating Temperature Range(Self-temperature rise is not included)	-40℃ to 85℃
Class of magnetic shield	Shielded (Ferrite Core)
Q(min.)	15
Q Test Frequency	25MHz
Self resonance frequency (min.)	95MHz
Brand	Murata
Series	LQM18NN_00

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ \text{download} \ the \ latest \ data sheet \ of \ LQM18NNR56K00\# \ from \ the \ of ficial \ website \ of \ Murata$


http://www.murata.com/en-us/products/productdetail?partno=LQM18NNR56K00%23


"#"at the end indicates the package specification code.



Characteristic Data

LQM18NNR56K00#





Impedance - Current Characteristics

Q-Frequency Characteristics

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



4 of 4