

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN12NG0Z# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN12NG0Z%23

## "#"at the end indicates the package specification code.

Size Code 1608 (0603) in mm (in inch), Wound Type

LQW18AN12NG0ZD




< List of part numbers with package codes > LQW18AN12NG0ZB LQW18AN12NG0ZD LQW18AN12NG0ZJ

# Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Consumer equipment,Automotiveinfotainment/comfort equipment,Medicalequipment [GHTF A/B/C] except forimplant & surgery & auto injector,Industrial equipment except fortransportation & facility & energyequipmentPlease refer to Our Website andspecifications, etc. for information aboutthe performance, functions, quality,management, and safety required forthe above applications, and useProducts after confirming theperformance and reliability of the actualProduct.	
Recommended	Automotive infotainment/comfort	
Applications	equipment	







(in mm)

1 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LQW18AN12NG0ZD

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ download \ the \ latest \ data sheet \ of \ LQW18AN12NG0Z\# \ from \ the \ of \ ficial \ website \ of \ Murata$ 

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN12NG0Z%23

### "#"at the end indicates the package specification code.



## References

		Standard
Packaging	Specifications	Packing Quantity
		Quantity
В	Bulk(Bag)	500
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

Mass (typ.)	
1 piece	0.003g

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

2 of 4



LQW18AN12NG0ZD

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ download \ the \ latest \ data sheet \ of \ LQW18AN12NG0Z\# \ from \ the \ official \ website \ of \ Murata$ 

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN12NG0Z%23

### "#"at the end indicates the package specification code.



## Specifications

L size	1.6±0.2mm
W size	0.8±0.2mm
T size	0.8±0.2mm
Size code inch (mm)	0603 (1608)
Inductance	12nH±2%
Inductance Test Frequency	100MHz
Rated current (Itemp) (Based on Temperature rise)	600mA
Max. of DC resistance	0.13Ω
Operating Temperature Range(Self-temperature rise is not included)	-55℃ to 125℃
Class of magnetic shield	Non-Shielded
Q(min.)	35
Q Test Frequency	250MHz
Self resonance frequency (min.)	6000MHz
Brand	Murata
Series	LQW18AN_0Z

### 3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN12NG0Z# from the official website of Murata


http://www.murata.com/en-us/products/productdetail?partno=LQW18AN12NG0Z%23

## "#"at the end indicates the package specification code.



LQW18AN12NG0ZD

**Characteristic Data** 



Inductance - Frequency Characteristics

## **Q-Frequency Characteristics**

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



4 of 4