

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN22NJ80# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN22NJ80%23

"#"at the end indicates the package specification code.

High Frequency Inductor with Low DC resistance and High Current Capability















## < List of part numbers with package codes >

LQW18AN22NJ80B

LQW18AN22NJ80D

LQW18AN22NJ80J




## **Applications**

Please be sure to read and comply with	
these "Precautions for use."	
Consumer equipment, Medical	
equipment [GHTF A/B/C] except for	
implant & surgery & auto injector,	
Industrial equipment except for	
transportation & facility & energy	
equipment	
Please refer to Our Website and	
specifications, etc. for information about	
the performance, functions, quality,	
management, and safety required for	
the above applications, and use	
Products after confirming the	
performance and reliability of the actual	
Product.	
Canadiana	
Consumer equipment	



# Appearance & Shape





1 of 5

#### Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN22NJ80# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN22NJ80%2

"#"at the end indicates the package specification code.



## References

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000

Mass (typ.)		
1 piece	0.0034g	

2 of 5

### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN22NJ80# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN22NJ80%2

"#"at the end indicates the package specification code.



# **Specifications**

L size	1.65±0.1mm
W size	0.99±0.1mm
T size	0.9±0.1mm
Size code inch (mm)	0603 (1608)
Inductance	22nH±5%
Inductance Test Frequency	100MHz
Rated current (Itemp) (Based on Temperature rise)	1300mA
Max. of DC resistance	0.086Ω
Operating Temperature Range(Self-temperature rise is not included)	-55°C to 125°C
Class of magnetic shield	Non-Shielded
Q(min.)	40
Q Test Frequency	250MHz
Self resonance frequency (min.)	3450MHz
Brand	Murata
Series	LQW18AN_80

3 of 5

### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN22NJ80# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=LQW18AN22NJ80%23

"#"at the end indicates the package specification code.




# Notice For General

In operating temperatures exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in the chart according to the operating temperature.

### Derating of Rated Current



4 of 5

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$ 



Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of LQW18AN22NJ80# from the official website of Murata


"#"at the end indicates the package specification code.





## Characteristic Data

LQW18AN22NJ80#

The charts below may show another part number which shares its characteristics.







5 of 5

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

