

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW5ATN331MQ2# from the official website of Murata

"#"at the end indicates the package specification code.

ww.murata.com/en-us/products/productdetail?partno=DLW5ATN331MQ2%23

DLW5ATN331MQ2#

In Production RoHS

REACH

< List of part numbers with package codes > DLW5ATN331MQ2B DLW5ATN331MQ2K

DLW5ATN331MQ2L




Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Medical	
	equipment [GHTF A/B/C] except for	
	implant & surgery & auto injector,	
	Industrial equipment except for	
	transportation & facility & energy	
	equipment	
Specific	Please refer to Our Website and	
Applications	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Consumer equipment	
Applications		



Appearance & Shape





Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
к	330mm Embossed Tape	2500
L	180mm Embossed Tape	700



Features

- 1. Low profile(h=2.35mm max.)
- 2. Small size(5.0x3.6mm)
- 3. Large Current Available (2Ato 6A)
- 4 · Operating Temperature Range: -40°C to +105°C
- 5. Reflow and Flow soldering Available

Application

Noise suppression for power line

- 1. Power line equipment
- DC/DC converter
- battery charger
- 2. Portable equipment
- PDA(Personal Digital Assistance) note PC printer DVC

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW5ATN331MQ2# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=DLW5ATN331MQ2%23

"#"at the end indicates the package specification code.



Specifications

DLW5ATN331MQ2#

Shape	SMD
Size Code (in mm)	5036
Size Code (in inch)	2014
Length	5.0mm
Length Tolerance	±0.3mm
Width	3.6mm
Width Tolerance	±0.3mm
Thickness	2.2mm
Thickness Tolerance	±0.15mm
Common Mode Impedance (at 100MHz)	330Ω
Common Mode Impedance (at 100MHz) Tolerance	(Тур.)
Common Mode Impedance (at 10MHz)	20Ω
Common Mode Impedance (at 10MHz) Tolerance	min.
Rated Current	4A
Derating of Rated Current	Yes (Over 85°C) *For details, please check the derating diagram.
Rated Voltage	100Vdc
Withstanding Voltage	250Vdc
DC Resistance(max.)	0.027Ω
DC Resistance	0.027Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40℃ to 105℃
Mass(typ.)	0.14g

Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Product Search Data Sheet



DLW5ATN331MQ2#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW5ATN331MQ2# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=DLW5ATN331MQ2%23

"#"at the end indicates the package specification code.






10000 Common mode DLW5ATN112MO 1000 DLW5ATN501M02 DLW5ATN331MQ2 Impedance (Ω) DLW5ATN151MQ2 DLW5ATN500M02 100 10 DLW5ATN151MQ2 DLW5ATN500MQ2 DLW5ATN501MQ2 DLWSATN112MQ2 Differential mode 100 10 1000 Frequency (MHz)

Impedance-Frequency Characteristics


In operating temperature exceeding +85°C, derating of current is necessary for DLW5AT series (105 degree C available type). Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Derating of Rated Current

Impedance-Frequency Characteristics (Main Items)



Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

