

BLM15KD121SN1#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of BLM15KD121SN1# from the official website of Murata

"#"at the end indicates the package specification code.









< List of part numbers with package codes > BLM15KD121SN1B

BLM15KD121SN1D

BLM15KD121SN1J




Applications

| Unsuitable | Please be sure to read and comply with | |
|--------------|--|--|
| Applications | these "Precautions for use." | |
| | Consumer equipment,Medical | |
| | equipment [GHTF A/B/C] except for | |
| | implant & surgery & auto injector, | |
| | Industrial equipment except for | |
| | transportation & facility & energy | |
| | equipment | |
| Specific | Please refer to Our Website and | |
| Applications | specifications, etc. for information about | |
| | the performance, functions, quality, | |
| | management, and safety required for | |
| | the above applications, and use | |
| | Products after confirming the | |
| | performance and reliability of the actual | |
| | Product. | |
| Recommended | Consumer equipment | |
| Applications | | |



Appearance & Shape













Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|------------------|---------------------------------|
| В | Bulk(Bag) | 1000 |
| D | 180mm Paper Tape | 10000 |
| J | 330mm Paper Tape | 50000 |



Features

- 1. The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
- 3.BLM15 maximum rated current 3.8A.
- It is effective in noise reduction at the communication frequency of 700MHz.

1 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





BLM15KD121SN1#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BLM15KD121SN1# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=BLM15KD121SN1%2

"#"at the end indicates the package specification code.



Specifications

| Shape | SMD |
|---------------------------------|----------------|
| Size Code (in inch) | 0402 |
| Length | 1.0mm |
| Length Tolerance | ±0.05mm |
| Width | 0.5mm |
| Width Tolerance | ±0.05mm |
| Thickness | 0.5mm |
| Thickness Tolerance | ±0.05mm |
| Operating Temperature Range | -55°C to 125°C |
| Mass(typ.) | 0.001g |
| Number of Circuit | 1 |
| Rated Current (at 85°C) | 1500mA |
| Rated Current (at 125°C) | 930mA |
| DC Resistance(max.) | 0.07Ω |
| Impedance (at 100MHz) | 120Ω |
| Impedance (at 100MHz) Tolerance | ±25% |
| Size Code (in mm) | 1005 |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




BLM15KD121SN1#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BLM15KD121SN1# from the official website of Murata


"#"at the end indicates the package specification code.






In operating temperature exceeding +85°C, derating of current is necessary for BLM15KD_SN1 series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics

Derating of Rated Current



Equivalent Circuit

3 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

