

## BLM18SP101SZ1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18SP101SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM18SP101SZ1%23

"#"at the end indicates the package specification code.









< List of part numbers with package codes > BLM18SP101SZ1B BLM18SP101SZ1D




### **Applications**

Unsuitable Applications  Please be sure to read and comply with these "Precautions for use."  Automotive infotainment/comfort equipment, Consumer equipment, Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector,Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Applications  Applications			
Automotive infotainment/comfort equipment, Consumer equipment, Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector, Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort	Unsuitable	Please be sure to read and comply with	
equipment, Consumer equipment, Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector, Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort	Applications	these "Precautions for use."	
Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector,Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort	'	Automotive infotainment/comfort	
except for implant & surgery & auto injector,Industrial equipment except for transportation & facility & energy equipment  Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort		equipment,Consumer equipment,	
Specific Applications  Specific Applications  Specific Applications  Specific Applications  Specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort		Medical equipment [GHTF A/B/C]	
Specific Applications  Transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort		except for implant & surgery & auto	
Specific Applications  equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort		injector,Industrial equipment except for	
Applications  Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort		transportation & facility & energy	
Applications  Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended  Automotive infotainment/comfort		equipment	
specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended Automotive infotainment/comfort		Please refer to Our Website and	
management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended Automotive infotainment/comfort		specifications, etc. for information about	
the above applications, and use Products after confirming the performance and reliability of the actual Product.  Recommended Automotive infotainment/comfort		the performance, functions, quality,	
Products after confirming the performance and reliability of the actual Product.  Recommended Automotive infotainment/comfort		management, and safety required for	
performance and reliability of the actual Product.  Recommended Automotive infotainment/comfort		the above applications, and use	
Product.  Recommended Automotive infotainment/comfort		Products after confirming the	
Recommended Automotive infotainment/comfort		performance and reliability of the actual	
		Product.	
Applications	Recommended	Automotive infotainment/comfort	
Applications	Applications	equipment	



### Appearance & Shape







### Packaging Information

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	1000
D	180mm Paper Tape	4000



#### **Features**

The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM18SP series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 6ADC.

1 of 3

#### Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BLM18SP101SZ1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18SP101SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM18SP101SZ1%2

"#"at the end indicates the package specification code.



## **Specifications**

Shape	SMD
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.005g
Number of Circuit	1
Rated Current (at 85°C)	3700mA
Rated Current (at 125°C)	2500mA
DC Resistance(max.)	0.022Ω
Impedance (at 100MHz)	100Ω
Impedance (at 100MHz) Tolerance	±25%
Size Code (in mm)	1608

2 of 3

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



## BLM18SP101SZ1#


Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18SP101SZ1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLM18SP101SZ1%23

"#"at the end indicates the package specification code.







In operating temperature exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics



**Derating of Rated Current** 

**Equivalent Circuit** 

3 of 3

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

