

information provided may not be the most current. Please download the latest datasheet of DXW21BN7511T# from the official website of Murata

Note: If you have not downloaded this document from our official website, please note that the

"#"at the end indicates the package specification code.

DXW21BN7511T#







< List of part numbers with package codes >

DXW21BN7511TB

DXW21BN7511TK

DXW21BN7511TL




Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Medical	
	equipment [GHTF A/B/C] except for	
	implant & surgery & auto injector,	
	Industrial equipment except for	
	transportation & facility & energy	
	equipment	
Specific	Please refer to Our Website and	
Applications	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Canalimar aguinment	
Applications	Consumer equipment	



Appearance & Shape







Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
К	330mm Embossed Tape	10000
L	180mm Embossed Tape	2000



Features

- 1. Ultra Miniature Wire Wound Transformer $(2.0 \times 1.2 \times 1.2 \text{mm})$
- 2. Low Insertion Loss
- 3. Wideband Frequency Range
- 4. Surface Mount

Applications

TV tuners, Cable TV tuners and Communication application that require unbalance mode to balance mode conversion.

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





DXW21BN7511T#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DXW21BN7511T# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=DXW21BN7511T%2

"#"at the end indicates the package specification code.



Specifications

Operating Temperature Range	-40°C to 85°C
Frequency Range	50MHz to 1200MHz
Insertion Loss	50 to 870MHz:1.0dB max.,870 to 1200MHz:1.2dB max.
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2mm
Length Tolerance	±0.2mm
Width	1.2mm
Width Tolerance	±0.2mm
Thickness	1.2mm
Thickness Tolerance	±0.2mm
Power Rating	27dBm
Rated Voltage	20Vdc
Withstanding Voltage	50Vdc
Port Impedance	75Ω - 75Ω
CMRR(min.)	20dB
DC Resistance(max.)	0.77Ω
Insulation Resistance(min.)	10ΜΩ
Mass(typ.)	0.011g

2 of 3

Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



^{1.} This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

^{2.} This datasheet has only typical specifications because there is no space for detailed specifications.

DXW21BN7511T#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.


Please download the latest datasheet of DXW21BN7511T# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=DXW21BN7511T%2

"#"at the end indicates the package specification code.








Insertion Loss Characteristics

CMRR Characteristics



Equivalent Circuit

3 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

