

BEI15-120-Q12N-C

Note: This datasheet may be out of date.

Please download the latest datasheet of BEI15-120-Q12N-C from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BEI15-120-Q12N-C







Applications

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
	Consumer equipment,Industrial
	Equipment
	Please refer to Our Website and
	specifications, etc. for information about
Specific	the performance, functions, quality,
Applications	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.



Features

±12V,±625mA, Dual Output Isolated 1"x1" DC-DC Converter, 9-36V Input Range, Negative Logic, Through-Hole



Appearance & Shape



1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





BEI15-120-Q12N-C

Note: This datasheet may be out of date.

Please download the latest datasheet of BEI15-120-Q12N-C from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BEI15-120-Q12N-C



Specifications

Output power (W)Max	15W
Vin(V)	9V to 36V
Vin(V)typ	24V
Vout(V)	12V
Vout(V)typ	12V
LineRegulation (%)	-0.25% to 0.25%
LoadRegulation (%)	-0.25% to 0.25%
Isolation Voltage (V)	2000V
Efficiency (%)	86%
Size(mm)W	24.4mm
Size(mm)L	27.9mm
Size(mm)T	8.4mm
Operatingtemperature(degC)	-40°C to 85°C
Outputs (#)	2
lout(A)Max	0.625A
Form	1 x 1
Package	DIP
Productseries	BEI
Product Series Features	Isolated Wide Input Bipolar 15- Watt DC-DC Converters
lout2(A)Max	-0.625A
Vout2 (V)	-12V
Vout2 (V)typ	-12V
Brand	Murata Power Solutions

2 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

