

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ download \ the \ latest \ data sheet \ of \ LQM21FN4R7M80\# \ from \ the \ official \ website \ of \ Murata$ 

http://www.murata.com/en/products/productdetail?partno=LQM21FN4R7M80%23

### "#"at the end indicates the package specification code.

Large Current, Low DC Resistance Type


LQM21FN4R7M80#




< List of part numbers with package codes > LQM21FN4R7M80B LQM21FN4R7M80K LQM21FN4R7M80L

# Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Medical	
	equipment [GHTF A/B/C] except for	
	implant & surgery & auto injector,	
	Industrial equipment except for	
	transportation & facility & energy	
	equipment	
Specific	Please refer to Our Website and	
Applications	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	O	
Applications	Consumer equipment	









(in mm)

1 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQM21FN4R7M80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQM21FN4R7M80%23

# LQM21FN4R7M80#

"#"at the end indicates the package specification code.



### References

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	1000
К	330Embossed Tape	10000
L	180Embossed Tape	3000

Mass (typ.)		
1 piece	0.016g	

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

2 of 4



LQM21FN4R7M80#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQM21FN4R7M80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQM21FN4R7M80%23

#### "#"at the end indicates the package specification code.



### Specifications

L size	2.0±0.2mm
W size	1.25±0.2mm
T size	1.25±0.2mm
Size code inch (mm)	0805 (2012)
Inductance	4.7µH±20%
Inductance Test Frequency	1MHz
Rated current (Isat) (Based on Inductance change)	120mA
Rated current (Itemp) (Based on Temperature rise)	120mA
Max. of DC resistance	0.234Ω
DC resistance	0.18Ω±30%
Operating Temperature Range(Self-temperature rise is not included)	-55℃ to 125℃
Class of magnetic shield	Shielded (Ferrite Core)
Self resonance frequency (min.)	25MHz
Brand	Murata
Series	LQM21FN_80

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



INNOVATOR IN ELECTRONICS

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQM21FN4R7M80# from the official website of Murata


http://www.murata.com/en/products/productdetail?partno=LQM21FN4R7M80%23


### "#"at the end indicates the package specification code.



## Characteristic Data

LQM21FN4R7M80#





Impedance - Current Characteristics

Impedance - Frequency Characteristics

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



4 of 4