

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN19NG80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partpo=LOW18AN19NG80%2

"#"at the end indicates the package specification code.

High Frequency Inductor with Low DC resistance and High Current Capability

















< List of part numbers with package codes >

LQW18AN19NG80B

LQW18AN19NG80D

LQW18AN19NG80J




### **Applications**

| Unsuitable   | Please be sure to read and comply with     |  |
|--------------|--|--|
| Applications | these "Precautions for use."               |  |
|              | Consumer equipment,Medical                 |  |
|              | equipment [GHTF A/B/C] except for          |  |
|              | implant & surgery & auto injector,         |  |
|              | Industrial equipment except for            |  |
|              | transportation & facility & energy         |  |
|              | equipment                                  |  |
| Specific     | Please refer to Our Website and            |  |
| Applications | specifications, etc. for information about |  |
|              | the performance, functions, quality,       |  |
|              | management, and safety required for        |  |
|              | the above applications, and use            |  |
|              | Products after confirming the              |  |
|              | performance and reliability of the actual  |  |
|              | Product.                                   |  |
| Recommended  | Consumer equipment                         |  |
| Applications |  |  |



## Appearance & Shape





1 of 5

#### Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN19NG80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18AN19NG80%23

"#"at the end indicates the package specification code.



### References

| Packaging | Specifications   | Standard<br>Packing<br>Quantity |
|-----------|------------------|---------------------------------|
| В         | Bulk(Bag)        | 500                             |
| D         | 180mm Paper Tape | 4000                            |
| J         | 330mm Paper Tape | 10000                           |

| Mass (typ.) |         |
|-------------|---------|
| 1 piece     | 0.0034g |

2 of 5

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN19NG80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18AN19NG80%23

"#"at the end indicates the package specification code.



## **Specifications**

| L size   | 1.65±0.1mm     |
|--|----------------|
| W size   | 0.99±0.1mm     |
| T size   | 0.9±0.1mm      |
| Size code inch (mm)  | 0603 (1608)    |
| Inductance   | 19nH±2%        |
| Inductance Test Frequency  | 100MHz         |
| Rated current (Itemp) (Based on Temperature rise)                  | 1400mA         |
| Max. of DC resistance  | 0.075Ω         |
| Operating Temperature Range(Self-temperature rise is not included) | -55°C to 125°C |
| Class of magnetic shield   | Non-Shielded   |
| Q(min.)  | 40             |
| Q Test Frequency   | 250MHz         |
| Self resonance frequency (min.)                                    | 4600MHz        |
| Brand  | Murata         |
| Series   | LQW18AN_80     |

3 of 5

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN19NG80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18AN19NG80%23

"#"at the end indicates the package specification code.




## Notice For General

In operating temperatures exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in the chart according to the operating temperature.

### Derating of Rated Current



4 of 5

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$ 



Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LQW18AN19NG80# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LQW18AN19NG80%23


"#"at the end indicates the package specification code.





### Characteristic Data

**LQW18AN19NG80#** 

The charts below may show another part number which shares its characteristics.







5 of 5

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

