

Note: This datasheet may be out of date.

Please download the latest datasheet of DLM11SN900HZ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLM11SN900HZ2%2

"#"at the end indicates the package specification code.









< List of part numbers with package codes > DLM11SN900HZ2B DLM11SN900HZ2L



Applications

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
Applications Specific Applications	these "Precautions for use." Automotive infotainment/comfort equipment,Consumer equipment, Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector,Industrial equipment except for transportation & facility & energy equipment Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.
Recommended	Automotive infotainment/comfort
Applications	equipment,USB2.0,LVDS




Packaging Information

Packaging	Specifications	Standard
		Packing
		Quantity
В	Bulk(Bag)	500
L	180mm Embossed Tape	4000



Appearance & Shape





1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLM11SN900HZ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLM11SN900HZ2%23

"#"at the end indicates the package specification code.



Features

- 1. Small size and tight dimensional tolerance Size:1.25x1.0x0.5mm Tolerance:+-0.1mm
- 2. High common mode impedance up to 90ohm (at 100MHz) is available.
- DLM11S series enables noise suppression for differential signal line without distortion in highspeed signal transmission due to its line impedance matching.
- 4. High Cut-off Frequency.

2 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLM11SN900HZ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLM11SN900HZ2%2

"#"at the end indicates the package specification code.



Specifications

Shape	SMD
Size Code (in mm)	1210
Size Code (in inch)	0504
Length	1.25mm
Length Tolerance	±0.1mm
Width	1.0mm
Width Tolerance	±0.1mm
Thickness	0.5mm
Thickness Tolerance	±0.1mm
Common Mode Impedance (at 100MHz)	90Ω
Common Mode Impedance (at 100MHz) Tolerance	±25%
Rated Current	100mA
Derating of Rated Current	No
Rated Voltage	5Vdc
Withstanding Voltage	12.5Vdc
DC Resistance(max.)	1.38Ω
DC Resistance	1.1Ω±25%
Insulation Resistance(min.)	100ΜΩ
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.004g
Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

3 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date.


Please download the latest datasheet of DLM11SN900HZ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLM11SN900HZ2%23


"#"at the end indicates the package specification code.








Impedance-Frequency Characteristics




Impedance-Frequency Characteristics (Main Items)

■ Equivalent Circuit (Note 1)



Note1: The Port/Pin No. of the Simulation Model provided by our company is



Equivalent Circuit

Differential Mode Transmission Characteristics (Typical Value)

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

4 of 4