

Product Search Data Sheet


LFD18829MMP2E093

In Production Recommended RoHS REACH

Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Industrial Equipment,Medical equipment [GHTF	
	A/B],Mobile Electronics	
	Please refer to Our Website and	
Oracifia	specifications, etc. for information about	
Specific Applications	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Consumer equipment,Industrial	
Applications	Equipment,Medical equipment [GHTF	
	A/B],Mobile Electronics	


Appearance & Shape



http://www.murata.com/en/products/productdetail?partno=LFD18829MMP2E093

Packaging Information

Packaging	Specifications	Standard Packing Quantity
-	180mm Paper Tape	4000



Adiplexer branching low and high band.

- 1. Low insertion loss.
- 2. Small size, low-profiled and light weight.
- 3. Absolutely no adjustment required.
- 4. Reflow solderable.

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LFD18829MMP2E093

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of LFD18829MMP2E093 from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=LFD18829MMP2E093

Specifications

Applications	LTE
Center Frequency(f1)	829.50MHz
Frequency Range(f1)	699.00MHz to 960.00MHz
Center Frequency(f2)	2200.00MHz
Frequency Range(f2)	1710.00MHz to 2690.00MHz
Insertion Loss I)(in f1)	0.67dB max. (at 25°C)
Insertion Loss II)(in f1)	0.77dB max. (-40 to +85°C)
Insertion Loss I)(in f2)	0.80dB max. (at 25℃)
Insertion Loss II)(in f2)	0.90dB max. (-40 to +85°C)
Attenuation(in f2)	20.0dB min.
Attenuation(in f1)	20.5dB min.
VSWR{P1}(in f1)	1.64 max.
VSWR{P2}(in f2)	1.74 max.
VSWR{P3}(in f1,f2)	(f1)1.64 max., (f2)1.74 max.
Power Capacity	2W
Operating Temperature Range	-40°C to 85°C
L x W (size)	1.60x0.80mm
Thickness(max.)	0.7mm

2 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

