Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of MYMGM5R012ELA5RN from the official website of Murata

MYMGM5R012ELA5RN

7.5V to 15V input voltage, 12A, Buck Converter with PMBus and 125degC Tj











Applications

| Unsuitable | Please be sure to read and comply with | |
|--------------|--|--|
| Applications | these "Precautions for use." | |
| | Consumer equipment,Industrial | |
| | Equipment | |
| | Please refer to Our Website and | |
| | specifications, etc. for information about | |
| Specific | the performance, functions, quality, | |
| Applications | management, and safety required for | |
| | the above applications, and use | |
| | Products after confirming the | |
| | performance and reliability of the actual | |
| | Product. | |
| | Processor [ASIC / FPGA / xPU],Optical | |
| Recommended | Backbone network, Optical Module, | |
| Applications | Server,Storage,Switch,Base Station, | |
| | Industrial Equipment | |



Features


Input voltage ranges from 7.5 to 15V Settable output voltage from 1.8 to 5V Up to 12A of output current Quick response to load change Size 10.5 x 9.0 x 5.0 mm High efficiency of 95.7% (max.) Over Current (OC) /Voltage (OV), Under Voltage (UV) protection and Over Temperature protection (OT) ON/OFF control (Positive logic) Power Good (PGOOD) signal PMBus interface available



Appearance & Shape







1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current. Please download the latest datasheet of MYMGM5R012ELA5RN from the official website of Murata

MYMGM5R012ELA5RN



Specifications

| lout(A)Max | 12A |
|----------------------------|---|
| Vin(V) | 7.5V to 15V |
| Vin(V)typ | 12V |
| Vout(V) | 1.8V to 5V |
| Vout(V)typ | 5V |
| LineRegulation (%) | -0.5% to 0.5% |
| LoadRegulation (%) | -0.5% to 0.5% |
| Outputs (#) | 1 |
| Efficiency (%) | 95.7% |
| Switching frequency (kHz) | 800kHz |
| Size(mm)W | 9.0mm |
| Size(mm)L | 10.5mm |
| Size(mm)T | 5.0mm |
| Operatingtemperature(degC) | -40°C to 105°C |
| Circuit topology | Buck(Step-down) |
| Package | SMD |
| Туре | Modules (integrated components) |
| Productseries | MYMGM |
| Product Series Features | MYMGM series which is POL (Point of Load) is single output MonoBK with PMBus |
| Brand | Murata |

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

