

## BLM03AG102SN1#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BLM03AG102SN1# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=BLM03AG102SN1%23

"#"at the end indicates the package specification code.







< List of part numbers with package codes >

BLM03AG102SN1B

BLM03AG102SN1D

BLM03AG102SN1J



### **Applications**


| Unsuitable   | Please be sure to read and comply with  |  |
|--------------|---|--|
| Applications | these "Precautions for use."  |  |
|              | Consumer equipment,Medical  |  |
|              | equipment [GHTF A/B/C] except for   |  |
|              | implant & surgery & auto injector,  |  |
|              | Industrial equipment except for   |  |
|              | transportation & facility & energy  |  |
|              | equipment   |  |
| Specific     | Please refer to Our Website and   |  |
| Applications | specifications, etc. for information about  |  |
|              | the performance, functions, quality,  |  |
|              | management, and safety required for   |  |
|              | the above applications, and use   |  |
|              | Products after confirming the   |  |
|              | performance and reliability of the actual   |  |
|              | Product.  |  |
| Recommended  | Canada and a subject to the subject |  |
| Applications | Consumer equipment  |  |



### Appearance & Shape









### Packaging Information

| Packaging | Specifications   | Standard Packing Quantity |
|-----------|------------------|---------------------------|
| В         | Bulk(Bag)        | 1000                      |
| D         | 180mm Paper Tape | 15000                     |
| J         | 330mm Paper Tape | 50000                     |



#### **Features**

The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_Aseries generates an impedance from the relatively low frequencies. Therefore BLM\_Aseries is effective in noise suppression in a wide frequency range (30MHz to several hundred MHz).

1 of 3

#### Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BLM03AG102SN1#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of BLM03AG102SN1# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=BLM03AG102SN1%2

"#"at the end indicates the package specification code.



## Specifications

| Shape                           | SMD            |
|---------------------------------|----------------|
| Size Code (in inch)             | 0201           |
| Length                          | 0.6mm          |
| Length Tolerance                | ±0.03mm        |
| Width                           | 0.3mm          |
| Width Tolerance                 | ±0.03mm        |
| Thickness                       | 0.3mm          |
| Thickness Tolerance             | ±0.03mm        |
| Operating Temperature<br>Range  | -55°C to 125°C |
| Mass(typ.)                      | 0.3mg          |
| Number of Circuit               | 1              |
| Rated Current (at 125°C)        | 100mA          |
| DC Resistance(max.)             | 2.5Ω           |
| Impedance (at 100MHz)           | 1000Ω          |
| Impedance (at 100MHz) Tolerance | ±25%           |
| Size Code (in mm)               | 0603           |

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





## BLM03AG102SN1#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.


Please download the latest datasheet of BLM03AG102SN1# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=BLM03AG102SN1%2

"#"at the end indicates the package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$ 

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

